

## Power Net-35-100



Power Net-35-100, Power analyzer

Code: M52622. DESCATALOGADO

> Protocol: Modbus/RTU

> Usefull diam.(mm): 35

> Communications: RS-485

> Max. Current (A): 100

### Specifications

#### AC power supply

Installation category	CAT III 300/520 Vac
Consumption	4.2 VA
Frequency	50...60Hz
Nominal voltage	400 Vc.a.(-15...+10%)

#### Mechanical characteristics

Size (mm) width x height x depth	166 x 79 x 46 (mm)
Envelope	Self-extinguishing VO plastic
Weight (kg)	0,33

#### Environmental characteristics

Protection class	IP 20
Relative humidity (without condensation)	5...95%
Working temperature	-10...+50 °C

#### Standards

Certifications	UL, VDE
Electrical safety, Maximum height (m)	2000
Electrical safety, Installation category	CAT III 300V / 520V, IEC 61010
Standards	IEC 664, UL 94, VDE 0414, VDE 0110, UL 94, IEC 801, IEC 348, IEC 571- 1, EN 61000-6-3, EN 61000-6-1, EN-61010-1

#### Current measurement circuit

Nominal current (In)	100 A
Phase current measuring range	10...100%
Permanent overload	1.2 In

#### Voltage measurement circuit

Frequency measuring range	45...65 Hz
Nominal voltage	300V Ph-N, 520V Ph-Ph
Insulation voltage	3 kV~
Maximum input voltage consumption	0,75 VA

#### Electrical characteristics

## Power Net-35-100



Code: M52622.

Insulation voltage, circuit

3 kVc.a.

### Electrical safety

Insulation

Double-insulated electric shock protection class II (IEC 61010-1)

### Measurement accuracy

Power factor measurement

0,5...1

Phase voltage measurement

0.5 %  $\pm 2$  digits

### Serial communication

Technology / Type

RS-485

It requires the following in the case of three-phase systems: 1 Power Net xx-xxx + 2 TC-Power Net xx-xxx. The Power Net system is based on the installation of a master unit (Power Net), with which the measurement is taken in the 3 voltage and neutral phases, and the L1 current is measured. To measure current L2 and L3, install 2 TC-Power Net units connected to the master unit. They feature RS-485 communications, using the Modbus/RTU protocol.