



TCB-420-70-100A

TCB-420-70-100A, Current transformer with converter 4 ... 20 mA

Code: M71021.

- > Inner diameter (mm): 70
- > Analog output: 4...20 mA
- > Measurement Range (A): 100
- > Input current: 100 A
- > Transformer type: Current transformer with 4 ... 20 mA converter

Description

- Built-in internal output power supply
- Needs an auxiliary power supply of 230 V ac
- Primary current: from 2.5 to 1500 A ac, depending on the type
- Secondary current: 4..20 mA
- Internal diameter / Busbar dimensions: from 35 to 105 mm

Application

Used in power lines to obtain a current proportional to the primary current rated at 4... 20 mA in the secondary



TCB-420-70-100A

Current transformer with converter 4 ... 20 mA

Code: M71021.

Specifications

Auxiliary power supply

Voltage	230 Vac
---------	---------

Mechanical characteristics

Size (mm) width x height x depth	196 x 110 x 33 (mm)
Weight (kg)	0,39

Environmental characteristics

Working temperature	-10°...+50 °C
---------------------	---------------

Specific technical characteristics of current sensors

Inner diameter Ø (mm)	70
Operating voltage	0,72 kV~ max.

Current measurement circuit

Nominal frequency	57 / 60 Hz
Primary current measurement	100 A
Permanent overload	1,5 In
Transformation ratio	4 ... 20 mA

Standards

Standards	IEC 44-1, UNE 21 088-1, IEC 664, VDE0110, VDE0414, UL 94, IEC 1010-1, EN 61010-1
-----------	--

Measurement accuracy

Accuracy	±1,5% In
----------	----------

TCB
Current transformer with converter 4...20 mA

CODE	TYPE	Measurement Range (A)	Inner diameter (mm)
Output internal supply 4...20 mA (230 Vac Auxiliary supply)			
M71011.	TCB-420-35-2.5A	2.5	35
M71012.	TCB-420-35-5A	5	35
M71013.	TCB-420-35-10A	10	35
M71014.	TCB-420-35-20A	20	35
M71015.	TCB-420-35-50A	50	35
M71016.	TCB-420-35-100A	100	35
M71017.	TCB-420-35-250A	250	35



TCB-420-70-100A

Current transformer with converter 4 ... 20 mA

Code: M71021.

CODE	TYPE	Measurement Range (A)	Inner diameter (mm)
M71021.	TCB-420-70-100A	100	70
M71022.	TCB-420-70-250A	250	70
M71023.	TCB-420-70-500A	500	70
M71024.	TCB-420-70-750A	750	70

For greater currents, use: transformer + transducer