



# Bridge LR PSDC

Bridge LR PSDC, LoRa to RS-485 converter with DC power supply,  
Code: D80111.

## Specifications

### DC power supply

Installation category	CAT III 300 V
Consumption	1 W
Nominal voltage	9 ... 36 Vdc

### Environmental characteristics

Protection class	IP 20
Relative humidity (without condensation)	5 ... 95 %
Working temperature	-10 ... +60 °C

### Mechanical characteristics

Envelope	Plastic UL 94 - V0 self-extinguishing
Fastening	DIN rail
Weight (kg)	0,08

### Communication Network

Protocol	Modbus RTU LoRa™ Private (P2P)
----------	--------------------------------

### Standards

Electrical safety, Maximum height (m)	2000
Standards	EN 61010-1, EN 61000-6-2, EN 61000-6-4

### Electrical safety

Insulation	Double-insulated electric shock protection class II (IEC 61010-1)
------------	---

### User interface

LED	3 LED
-----	-------

### Radio communication -Antenna

	Tilttable omnidirectional SMA antenna
--	---------------------------------------

### Radio communication

Band	Banda ISM de 868 Mhz (9 canales)
------	----------------------------------

### Serial communication

Technology / Type	RS-485
-------------------	--------

### Bridge LR



# Bridge LR PSDC

Code: D80111.

LoRa™ / RS-485 Converter (Modbus/RTU)

CODE	TYPE	Description
LoRa		
D80110.	Bridge LR PSAC	LoRa to RS-485 Converter (Modbus/RTU) . AC power supply (110...264 Vac)
D80111.	Bridge LR PSDC	LoRa to RS-485 Converter (Modbus/RTU) . DC power supply (9 ... 36 Vdc)



## Bridge LR PSDC

Code: D80111.

### Dimensions



### Connections

