



FETC144 110V, Phasemeter

Code: M1344D. DESCATALOGADO

> Scale: 90° P1

> System: Balanced three-phase

> Accuracy: 1,5

> Measurement Range (V): 110

> Modules: 144x144

Description

- O Does not need an auxiliary power supply
- $\circ~$ DIN box with dimensions 96 and 144 mm
- o Class 1.5
- o Built-in electronic converter
- o Balanced single and three-phase circuits

Application

Measurement of $\mbox{cos}\phi$ in balanced or unbalanced single and three-phase circuits.







Phasemeters

Code: M1344D.

Specifications

Size (mm) width x height x depth	144 x 144 x 71.8 (mm)		
Fastening	Panel		
Weight (kg)	0,69		
invironmental characteristics			
Protection class	Panel: IP 52 (Front), IP 00 (Terminals)		
Storage temperature	-25+40 °C		
Working temperature	+10 +30 °C		
Standards			
Certifications	CE		
Electrical safety, Maximum height (m)	2000		
Standards	BS 89, UNE-EN 60051, IEC 144, DIN 43780, IEC 51, UNE 21318		
Current measurement circuit Consumption	1,5 VA		
Sampling frequency	20 100 Hz		
Nominal current (In)	5 A		
Allowable overload	1,2 In permanent / 5 In during 30s / 10 In during 5s / 40 In during 1s		
/oltage measurement circuit			
Consumption	1 VA		
Sampling frequency	40 70 Hz		
Maximum permanent measurement voltage	1,2 Vn permanent rated voltage / 2 Vn during 5s		
Electrical characteristics			
Insulation voltage, circuit	2 kV, 50 Hz, 1 min entre mecanismo y caja		
Measurement accuracy			
Accuracy	± 1,5 % FE		

FEMC / FETC

Single phase and three-phase 90° electronic phase-meters

CODE	TYPE	Scale	Accuracy	Modules	
Single-phase					
M13434.	FEMC96 110V	90° P1	1,5	96x96	







Phasemeters

Code: M1344D.

Current range: 0.1 to 1.2 ln. For the connection of transformers .../5A. Built-in electronic transducer.







Phasemeters

Code: M1344D.

Dimensions Connections



