



## SMC144 500V

SMC144 500V, Synchronoscope

Code: M14444. DESCATALOGADO

- > System: Single-phase
- > Accuracy: 1,5
- > Measurement Range (V): 500
- > Device: SMC144
- > Modules: 144x144

### Description

- Does not need an auxiliary power supply
- DIN box with dimensions: 96 and 144 mm
- Class 1
- For single and three-phase circuits
- Does not need an auxiliary power supply
- DIN box with dimensions: 72 and 96 mm
- Class 1.5
- Built-in voltage relay
- Low consumption

### Application

To provide a correct reading of the difference between the frequency and phase angle between two generators or a generator and the network, when connected in parallel. When the difference is zero, the instrument's needle does not move from the synchronization mark located in the centre of the scale.

The instrument scale is divided in two areas marked with the (+) and (-) signs. These signs indicate whether the machine being connected has a higher or lower frequency than the other one, respectively. Synchronism is achieved when the needle is on the (-) side, slowly turning towards (+). The needle of the instrument starts to turn in the correct direction when the difference in frequencies is 1.5 Hz for three-phase systems or 0.5 Hz for single-phase systems.



# SMC144 500V

Synchronization and marine applications equipment

Code: M14444.

## Specifications

### Electrical characteristics

Frequency	50 Hz.
Permanent overload	1,2 Un

### Mechanical characteristics

Size (mm) width x height x depth	144 x 144 x 102 (mm)
Fastening	Panel
Weight (kg)	2,25

### Environmental characteristics

Operating temperature	+10 ... +30 °C
-----------------------	----------------

### Standards

Electrical safety, Maximum height (m)	2000
---------------------------------------	------

SMC / STC  
Synchroscope

CODE	TYPE	Accuracy	Modules	Device
Three-phase				
M14435.	STC96 110V	1,5	96x96	STC96




## SMC144 500V

Synchronization and marine applications equipment

Code: M14444.


### Connections

#### Esquemas de conexión Connections diagrams




Connection:  
Conexión:

Voltage transf.  
Transf. Tensión



Directa / Direct

#### Monofásico (400,440,500 V) Single-phase



Voltage transf.  
Transf. Tensión