

CVE-A-AP, Transducer Vac.

Code: M25021.

- > Output type: 1
- > Analog output: 0...20mA
- > Measure: 230 Vac
- > Paramètre: V ~

Description

The CVE-A and CVE-AP transducers, convert A.C voltage to D.C process indicator signal.

The analog output is directly proportional to the input signal, calibrated as a RMS with sinus signal of 50Hz.

Circutor



Narrow section AC Voltage transducer

Code: M25021.

Specifications

AC power supply			
Nominal voltage	05, 10 Vcc		
Mechanical characteristics			
Size (mm) width x height x depth	20 x 70 x 110 (mm)		
Weight (kg)	0,054		
Environmental characteristics			
Protection class	IP 20 (Terminals) IP 40 (case)		
Storage temperature	-40+70 °C		
Working temperature	-10+60 °C		
Voltage measurement circuit			
Consumption	2,5 VA		
Frequency measuring range	45/65 Hz		
Voltage measuring range	70110 % Vn		
Nominal voltage	0660 V		
Maximum permanent measurement voltage	120 % Vn		
Standards			
Electrical safety, Maximum height (m)	2000		
Standards	IEC 529, IEC 688, IEC 801, EN 50081-1, EN 50082-1, IEC 1010		
Analogue inputs			
Load impedance in current	< 500 Ω		
Ripple (effective RMS value)	< 2 %		
Load impedance in voltage	> 500 Ω		
Response time	< 300 ms (099 % Vn)		
Analogue outputs			
Current mode, nominal range	010, 20 mAac		
Voltage mode: nominal output range	05, 10 Vac		
Measurement accuracy			
Phase current measurement	0,5 % FS		

CVE

Narrow section AC Voltage transducer

Circutor



Narrow section AC Voltage transducer

Code: M25021.

CODE	TYPE	Output type	Analog output	System	Measure	Paramètre
AC Voltage tr	ansducer					
M25011.	CVE-A	2	420mA	-	300 Vac	V ~
M25021.	CVE-A-AP	1	020mA	-	230 Vac	V ~

Specify ACCORDING TO THE CODE TABLE: 1. Code / 2. Input range / 3. Output range / 4. Auxiliary power supply / 5. Specify the network voltage for CFE-AP. xxx-AP types external auxiliary supply not required. 4...20 mA output not possible.

For other values, see coding table on following pages





Narrow section AC Voltage transducer

Code: M25021.

Dimensions

Connections

×

×

