



## CPF-M Out1,3

CPF-M Sal.1,3

Code: M25311. (CONSULTAR DISPONIBILIDAD)

- > Transducer FP
- > Output type: 1
- > 3
- > Analog output: 0...20mA
- > System: Single-phase

### Description

The **CPF** transducers measure power factor single phase.

The analog output is directly proportional to the measurement signal, 0...20 mA or 4...20 mA. The analog output can be bidirectional.



## CPF-M Out1,3

Power factor transducer

Code: M25311.

### Specifications

#### AC power supply, insulation

Pulse test (kV)	4 kV (1,2/50 $\mu$ s)
Test voltage (kV)	3 kV RMS 50 Hz 1min

#### AC power supply

Consumption	2,5 VA
Frequency	40...90 Hz
Nominal voltage	24/115/230/400 Vca (-15...+20 %)

#### DC power supply, insulation

Pulse test (kV)	3 kV (1,2/50 $\mu$ s)
Test voltage (kV)	2 kV RMS 50Hz 1 min

#### DC power supply

Consumption	2,5 VA
Nominal voltage	9-18 / 18-36 Vdc 36-72 / 90-140 Vdc

#### Mechanical characteristics

Size (mm) width x height x depth	95 x 72 x 110 (mm)
Weight (kg)	0,2

#### Environmental characteristics


Protection class	IP 20 (Terminals) IP 40 (case)
Storage temperature	-40...+70 °C
Working temperature	-10...+55 °C

#### Current measurement circuit

Nominal current (In)	5A
Phase current measurement	0,5...6 In
Allowable overload	300 % In permanent

#### Voltage measurement circuit

Consumption	0,2 VA
Frequency measuring range	45...65 Hz
Voltage measuring range	10...150 % Vn
Nominal voltage	500 Vca
Maximum permanent measurement voltage	1000 V



## CPF-M Out1,3


Power factor transducer

Code: M25311.

### Standards

Electrical safety, Maximum height (m)

2000



## CPF-M Out1,3

Power factor transducer

Code: M25311.

Standards

IEC 529, IEC 688, IEC 801, EN 50081-2, EN 50082-2, IEC 1010

### Analogue inputs


Load impedance in current	< 500 $\Omega$
Ripple (effective RMS value)	< 0,5 %
Response time	< 500 ms (0...99 % Vn)

### Analogue outputs

Current mode, nominal range	0...20 mAac / 4...20 mAac
-----------------------------	---------------------------

### Measurement accuracy

Phase current measurement	0,5 % FS
---------------------------	----------



## CPF-M Out1,3

---

Power factor transducer

Code: M25311.

## Dimensions

---

