



CPF-TEN Sal.1,3

Code: M25331. DESCATALOGADO

> Transducer FP> Output type: 1

> 3

> Analog output: 0...20mA

> System: Balanced three-phase (4 wires)

Description

The **CPF** transducers measure power factor single phase.

The analog output is directly proportional to the measurement signal, 0...20 mA or 4...20 mA. The analog output can be bidirectional.







Power factor transducer

Code: M25331.

Specifications

Pulse test (kV)	4 kV (1,2/50μs)	
Test voltage (kV)	3 kV RMS 50 Hz 1min	
AC power supply		
Consumption	2,5 VA	
Frequency	4090 Hz	
Nominal voltage	24/115/230/400 Vca (-15+20 %)	
DC power supply, insulation		
Pulse test (kV)	3 kV (1,2/50µs)	
Test voltage (kV)	2 kV RMS 50Hz 1 min	
DC power supply		
Consumption	2,5 VA	
Nominal voltage	9-18 / 18-36 Vdc 36-72 / 90-140 Vdc	
Mechanical characteristics		
Size (mm) width x height x depth	95 x 72 x 110 (mm)	
Weight (kg)	0,31	
Environmental characteristics		
Protection class	IP 20 (Terminals) IP 40 (case)	
Storage temperature	-40+70 °C	
Working temperature	-10+55 °C	
Current measurement circuit		
Nominal current (In)	5A	
Phase current measurement	0,56 In	
Allowable overload	300 % In permanent	
Voltage measurement circuit		
Consumption	0,2 VA	_
Frequency measuring range	4565 Hz	
Voltage measuring range	10150 % Vn	
Nominal voltage	500 Vca	
Maximum permanent measurement voltage	1000 V	









Power factor transducer

Code: M25331.

Standards

Electrical safety, Maximum height (m)

2000







Power factor transducer

Code: M25331.

Standards	IEC 529, IEC 688, IEC 801, EN 50081-2, EN 50082-2, IEC 1010
Analogue inputs	
Load impedance in current	< 500 Ω
Ripple (effective RMS value)	< 0,5 %
Response time	< 500 ms (099 % Vn)
Analogue outputs	
Current mode, nominal range	020 mAac / 420 mAac
Measurement accuracy	
Phase current measurement	0,5 % FS







Power factor transducer

Code: M25331.

Dimensions



