



## CFE-AP

CFE-AP, Transducer Hz

Code: M25521.

- > Output type: 1
- > Analog output: 0...20mA
- > System: Selecting Network voltage: 115 / 240 / 400 Vac
- > Measure: 45 ..... 55 Hz

## Description

The **CFE** and **CFE-AP** transducers, convert input frequency to D.C process indicator signal.

The analog output is directly proportional to the input frequency.



## CFE-AP

Narrow section AC frequency transducer

Code: M25521.

### Specifications

#### AC power supply

Nominal voltage	0...5, 10 Vcc
-----------------	---------------

#### Mechanical characteristics

Size (mm) width x height x depth	20 x 70 x 110 (mm)
Weight (kg)	0,19

#### Environmental characteristics

Protection class	IP 20 (Terminals) IP 40 (case)
Storage temperature	-40...+70 °C
Working temperature	-10...+60 °C

#### Voltage measurement circuit

Consumption	2,5 VA
Voltage measuring range	70...110 % Vn
Maximum permanent measurement voltage	120 % Vn

#### Standards

Electrical safety, Maximum height (m)	2000
Standards	IEC 529, IEC 688, IEC 801, EN 50081-1, EN 50082-1, IEC 1010

#### Analogue inputs

Load impedance in current	< 500 Ω
Ripple (effective RMS value)	< 1 %
Load impedance in voltage	> 500 Ω
Response time	< 300 ms (0...99 % Vn)

#### Analogue outputs

Current mode, nominal range	0...10, 20 mAac
Voltage mode: nominal output range	0...5, 10 Vac

#### Measurement accuracy

Phase current measurement	0,5 % FS
---------------------------	----------

#### CFE

Narrow section AC frequency transducer



## CFE-AP

Narrow section AC frequency transducer

Code: M25521.

CODE	TYPE	Output type	Analog output	System	Measure
<b>Frequency transducers</b>					
M25511.	CFE	2	4...20mA	Network voltage	45 ..... 55 Hz
M25521.	CFE-AP	1	0...20mA	Selecting Network voltage	45 ..... 55 Hz

Specify ACCORDING TO THE CODE TABLE: 1. Code / 2. Input range / 3. Output range / 4. Auxiliary power supply / 5. Specify the network voltage for CFE-AP. xxx-AP types external auxiliary supply not required. 4...20 mA output not possible.

**For other values, see coding table on following pages**



## CFE-AP

Narrow section AC frequency transducer

Code: M25521.

## Dimensions



## Connections

