,

Code:

Specifications

AC power supply

Installation category	CAT III 300/520 Vac
Consumption	4.2 VA
Frequency	50...60Hz
Nominal voltage	400 Vc.a.(-15...+10%)

Mechanical characteristics

Size (mm) width x height x depth	166 x 79 x 46 (mm)
Envelope	Self-extinguishing V0 plastic
Weight (kg)	0,33

Environmental characteristics

Protection class	IP 20
Relative humidity (without condensation)	5...95%
Working temperature	-10...+50 °C

Standards

Certifications	UL, VDE
Electrical safety, Maximum height (m)	2000
Electrical safety, Installation category	CAT III 300V / 520V, IEC 61010
Standards	IEC 664, UL 94, VDE 0414, VDE 0110, UL 94, IEC 801, IEC 348, IEC 571- 1, EN 61000-6-3, EN 61000-6-1, EN-61010-2

Current measurement circuit

Nominal current (In)	250 A
Phase current measuring range	10...100%
Permanent overload	1.2 In

Voltage measurement circuit

Frequency measuring range	45...65 Hz
Nominal voltage	300V Ph-N, 520V Ph-Ph
Insulation voltage	3 kV~
Maximum input voltage consumption	0,75 VA

Electrical characteristics

Insulation voltage, circuit	3 kVc.a.

Electrical safety

Insulation	Double-insulated electric shock protection class II (IEC 61010-1)

Creation date: 20/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



Code:

Measurement accuracy

Power factor measurement	0,5...1
Phase voltage measurement	0.5 % ±2 digits

Serial communication

Technology / Type	RS-485

It requires the following in the case of three-phase systems: 1 Power Net xx-xxx + 2 TC-Power Net xx-xxx. The Power Net system is based on the installation of a master unit (Power Net), with which the measurement is taken in the 3 voltage and neutral phases, and the L1 current is measured. To measure current L2 and L3, install 2 TC-Power Net units connected to the master unit. They feature RS-485 communications, using the Modbus/RTU protocol.

Creation date: 20/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.