



CVM-C5-ITF-485-C

CVM-C5-ITF-485-C, Power analyzer

Code: M55884. DESCATALOGADO

- > Protocol: Modbus/RTU
- > Communications: RS-485
- > Transistor output: 1
- > Measuring current Channels: 3
- > Input current: .../5 A | .../1 A
- > Mounting: Pannel
- > Modules: 96 x 96

Description

The **CVM-C5** is a panel mounted (96 x 96 mm) multimeter that records energy values. Compact and intuitive, with 4-quadrant measurement (Consumption and Generation). The **CVM-C5** is suitable for Low Voltage installations, in both 3 and 4-wire three-phase circuits, two-phase circuits with or without neutral, single-phase circuits or ARON connections.

Display features and interface:

- Quick display of parameters with a single button
- Clearly displays the electric parameters of the installation
- Displays the electricity consumption value according to the cost per kWh
- kgCO₂ consumption/generation indicator or according to the energy source
- Backlit LCD screen
- Operating hour indicator for preventive maintenance.

Other features:

- Modbus/RS-485 communications (optional)
- Measurement with **CIRCUITOR's MC** efficient current transformers or .../5 A, .../1 A or .../333 mV transformers.
- 1 digital output (SO interface)
- 1 digital input (tariff or energy source selection)
- Maximum, minimum values and maximum demand.

Application

- Recording and displaying the consumption of energy from two different sources (network/generator set).
- Generation of an impulse signal associated with the cost, kgCO₂ emissions or savings, according to the consumption or generation of energy.
- Generation of alarms with a transistor output; configurable parameters: Low/High, hysteresis (%), NO/NC, connection/disconnection delay and interlocking.



CVM-C5-ITF-485-C

Multifunctional multimeter for panel

Code: M55884.

Specifications

AC power supply

| | |
|-----------------------|----------------------|
| Installation category | CAT III 300 V |
| Consumption | 3.5 ... 6 VA |
| Frequency | 50 ... 60 Hz |
| Nominal voltage | 95 ... 240 V ~ ± 10% |

DC power supply

| | |
|-----------------------|-----------------------|
| Installation category | CAT III 300 V |
| Consumption | 2 ... 6 W |
| Nominal voltage | 105 ... 272 Vdc ± 10% |

Mechanical characteristics

| | |
|----------------------------------|-------------------------------|
| Size (mm) width x height x depth | 96 x 96 x 60.9 (mm) |
| Envelope | Self-extinguishing V0 plastic |
| Fastening | Panel |
| Weight (kg) | 0,237 |

Environmental characteristics

| | |
|--|-----------------------------|
| Protection class | IP 51 (Front), IP 20 (rear) |
| Relative humidity (without condensation) | 5...95% |
| Storage temperature | -10... +50 °C |
| Working temperature | -5...+45 °C |

Standards

| | |
|---------------------------------------|--|
| Certifications | UL/CSA 61010-1 3rd edition |
| Electrical safety, Maximum height (m) | 2000 |
| Standards | IEC 61010, UNE EN 61000-6-2, UNE EN 61000-6-4, |

Current measurement circuit

| | |
|-------------------------------|------------------|
| Installation category | CAT III 300 V |
| Nominal current (In) | .../5A , .../1 A |
| Phase current measuring range | 5...110% In |
| Maximum pulse current | 100 A |
| Minimum current measurement | 10 mA |

Voltage measurement circuit

| | |
|---------------------------|---------------|
| Installation category | CAT III 300 V |
| Frequency measuring range | 45 ... 65 Hz |
| Voltage measuring range | 5 ...120% Un |



CVM-C5-ITF-485-C

Multifunctional multimeter for panel

Code: M55884.

| | |
|--------------------------------------|-----------------------|
| Nominal voltage | 300V Ph-N, 520V Ph-Ph |
| Minimum measurement voltage (Vstart) | 10 V Ph-N |

User interface

| | |
|---------------------------|----------|
| Keyboard | 3 keys |
| Display type | LCD |
| Visible display area size | 60X54 mm |

Digital transistor outputs

| | |
|--|---------------|
| Pulse width | 100 ms |
| Quantity | 1 |
| Type | NPN |
| Pulse output, time period (Ton / Toff) | 100 ms/100 ms |
| Maximum frequency | 5 imp / s |
| Maximum current | 50 mA |
| Maximum voltage | 24 Vdc |

Measurement accuracy

| | |
|---------------------------|-------|
| Phase voltage measurement | 0,50% |
|---------------------------|-------|

Serial communication

| | |
|-------------------|------------|
| Protocol | ModBus RTU |
| Technology / Type | RS-485 |

4-quadrant measuring unit. Can be used to program the voltage transformer ratio



CVM-C5-ITF-485-C

Multifunctional multimeter for panel

Code: M55884.

Dimensions

