



CVM-C5-MC-485-C

CVM-C5-MC-485-C

Code: M55894. DESCATALOGADO

- > Power analyzer
- > Protocol: Modbus/RTU
- > Communications: RS-485
- > Transistor output: 1
- > Digital inputs: 0
- > Measuring current Channels: 3
- > Input current: .../250 mA
- > Mounting: Pannel

Description

The **CVM-C5** is a panel mounted (96 x 96 mm) multimeter that records energy values. Compact and intuitive, with 4-quadrant measurement (Consumption and Generation). The **CVM-C5** is suitable for Low Voltage installations, in both 3 and 4-wire three-phase circuits, two-phase circuits with or without neutral, single-phase circuits or ARON connections.

Display features and interface:

- Quick display of parameters with a single button
- Clearly displays the electric parameters of the installation
- Displays the electricity consumption value according to the cost per kWh
- kgCO₂ consumption/generation indicator or according to the energy source
- Backlit LCD screen
- Operating hour indicator for preventive maintenance.

Other features:

- Modbus/RS-485 communications (optional)
- Measurement with **CIRCUTOR's MC** efficient current transformers or .../5 A, .../1 A or .../333 mV transformers.
- 1 digital output (SO interface)
- 1 digital input (tariff or energy source selection)
- Maximum, minimum values and maximum demand.

Application

- Recording and displaying the consumption of energy from two different sources (network/generator set).
- Generation of an impulse signal associated with the cost, kgCO₂ emissions or savings, according to the consumption or generation of energy.
- Generation of alarms with a transistor output; configurable parameters: Low/High, hysteresis (%), NO/NC, connection/disconnection delay and interlocking.



CVM-C5-MC-485-C

Multifunctional multimeter for panel

Code: M55894.

Specifications

AC power supply

Installation category	CAT III 300 V
Consumption	3.5 ... 6 VA
Frequency	50 ... 60 Hz
Nominal voltage	95 ... 240 V ~ ± 10%

DC power supply

Installation category	CAT III 300 V
Consumption	2 ... 6 W
Nominal voltage	105 ... 272 Vdc ± 10%

Mechanical characteristics

Size (mm) width x height x depth	96 x 96 x 60.9 (mm)
Envelope	Self-extinguishing V0 plastic
Fastening	Panel
Weight (kg)	0,22

Environmental characteristics

Protection class	IP 51 (Front), IP 20 (rear)
Relative humidity (without condensation)	5...95%
Storage temperature	-10... +50 °C
Working temperature	-5...+45 °C

Standards

Certifications	UL/CSA 61010-1 3rd edition
Electrical safety, Maximum height (m)	2000
Standards	IEC 61010, UNE EN 61000-6-2, UNE EN 61000-6-4,

Current measurement circuit

Installation category	CAT III 300 V
Nominal current (In)	.../250A
Phase current measuring range	5...110% In
Maximum pulse current	100 A
Minimum current measurement	0,25 A (MC1) / 0,12 A (MC3)

Voltage measurement circuit

Installation category	CAT III 300 V
Frequency measuring range	45 ... 65 Hz
Voltage measuring range	5 ...120% Un



CVM-C5-MC-485-C

Multifunctional multimeter for panel

Code: M55894.

Nominal voltage	300V Ph-N, 520V Ph-Ph
Minimum measurement voltage (Vstart)	10 V Ph-N

User interface

Keyboard	3 keys
Display type	LCD
Visible display area size	60X54 mm

Digital transistor outputs

Pulse width	100 ms
Quantity	1
Type	NPN
Pulse output, time period (Ton / Toff)	100 ms/100 ms
Maximum frequency	5 imp / s
Maximum current	50 mA
Maximum voltage	24 Vdc

Measurement accuracy

Phase voltage measurement	0,50%
---------------------------	-------

Serial communication

Protocol	ModBus RTU
Technology / Type	RS-485

4-quadrant measuring unit. Can be used to program the voltage transformer ratio



CVM-C5-MC-485-C

Multifunctional multimeter for panel

Code: M55894.

Dimensions

