

CVM-C10-FLEX-IN-485-ICT2

Code: M55961. DESCATALOGADO

> Power analyzer

> Mounting: Pannel

#### Description

Compact and versatile power analyser, with 4-quadrant measurement (Consumption and Generation), suitable for High, Medium and Low-Voltage installations, since it can process high voltage:current transformation ratios of up to 2000 A. Measures current with flexible Rogowski sensors.

Capable of adapting to any type of electrical network topology, from single-phase lines, two-phase lines with or without neutral to three-phase lines with or without Neutral. The **CVM-C10-Flex** calculates the sensitivity of the measurement range scale automatically, according to the nominal value of the detected current, up to a full-scale of 2000 A. (Twice the full-scale value of measured current, 1000 A).

The flexible sensors feature a magnetic lock, which allows the sensors to be sealed. They are robust and can withstand frequent assembly and disassembly procedures, thanks to these magnetic lock.

Quick installation on distribution panels or switchboards of the unit, thanks to its flexible current sensors. Self-adjustment of the scale sensitivity. Does not require the current primary to be programmed. (1000 A by default, factory setting). Remote correction of errors associated with the incorrect connection of the unit to the electrical installation via remote communication systems (PowerStudio).

Display features and interface:

- Backlit keypad (capacitive)
- $\circ~$  Analogue display for instantaneous parameters (power, maximum power reached and cos  $\phi$  or PF)
- Backlit display
- Cost by tariff

Operating time indicator for preventive maintenance.

- The unit has the following functions:
- Recording of the energy consumption from three different sources: network, generator set or photovoltaic energy generation system.
- o Selection of tariffs with digital inputs. Perfect for calculating costs in three different work shifts.

#### Application

- Management Systems that require roaming measuring points.
- Distribution panels or switchboards that cannot stop the installation of a measuring unit.

Circutor



Panel-mounted power analyser with flexible Rogowski sensors

Code: M55961.

#### Specifications

AC power supply	
Installation category	CAT III 300 V
Consumption	4 6 VA
Frequency	50 60 Hz
Nominal voltage	95 240 V ~ ± 10%
DC power supply	
Installation category	CAT III 300 V
Mechanical characteristics	
Size (mm) width x height x depth	96 x 96 x 60.9 (mm)
Envelope	Self-extinguishing VO plastic
Fastening	Panel
Weight (kg)	0,322
Environmental characteristics	
Protection class	IP 51 (Front), IP 64 (with accessory), IP 21 (rear)
Relative humidity (without condensation)	5 95%
Storage temperature	-10 +50 °C
Working temperature	-5 +45 °C
Standards	
Certifications	UL/CSA 61010-1 3rd edition, UL, VDE
Electrical safety, Maximum height (m)	2000
Standards	UNE EN 61010, UNE EN 61000-6-3, UNE EN 61000-6-1, IEC 664, VDE 0110, UL 94 BS EN 61000-6-2, BS EN 61000-6-5
Current measurement circuit	
Installation category	CAT III 300 V
Nominal current (In)	/100 mV c.a
Neutral current measurement	/100 mV~
Phase current measuring range	0.2 200% In
Maximum input current consumption	0,9 VA
Maximum pulse current	2 In
Minimum current measurement	0,2 mV ac
Voltage measurement circuit	
Installation category	CAT III 300 V
Frequency measuring range	45 65 Hz

Circutor



Panel-mounted power analyser with flexible Rogowski sensors

#### Code: M55961.

Voltage measuring range	5120% Un
Nominal voltage	300V Ph-N, 520V Ph-Ph
Minimum measurement voltage (Vstart)	15 V
User interface	
LED	3 LED
Keyboard	3 keys
Display type	LCD Custom COG
Digital inputs	
Input/output insulation	Optoisolated
Quantity	3
Туре	NPN Potential-free contact
Digital relay outputs	
Electrical life (at maximum load)	60x10 <sup>3</sup> cycles
Mechanical life	10x10 <sup>6</sup> cycles
Maximum switching capacity	1500 VA
Serial communication	
Protocol	ModBus/RTU, BACnet

# Circutor



Panel-mounted power analyser with flexible Rogowski sensors

Code: M55961.

## Dimensions

# Connections

×

×

