



M-CVM-AB-8I-80TR

M-CVM-AB-8I-80TR, Expansion module

Code: M56E01.

- > Memory: No
- > Transistor output: 8
- > Digital inputs: 8

Description

Expansion module with 8 digital inputs and 8 transistor outputs.

Application

Digital inputs

- Reports via communications:
- Logic states of non-unit external systems
- Metering of the impulses generated by other units (water and gas meters, etc.)

Digital outputs

- Activation / deactivation by maximum or minimum instantaneous parameter values measured by the unit
- Generation of impulses by incremental parameters measured by the unit



M-CVM-AB-8I-80TR

Expansion modules M-CVM-AB-8I-80TR

Code: M56E01.

Specifications

DC power supply

| | |
|-------------|----------|
| Consumption | max. 3 W |
|-------------|----------|

Mechanical characteristics

| | |
|----------------------------------|-------------------------------|
| Size (mm) width x height x depth | 90 x 90 x 90 (mm) |
| Envelope | Self-extinguishing V0 plastic |
| Fastening | Panel |
| Weight (kg) | 0,156 |

Environmental characteristics

| | |
|--|---------------|
| Protection class | IP 30 |
| Relative humidity (without condensation) | 5 ... 95% |
| Storage temperature | -20... +80 °C |
| Working temperature | -10...+50 °C |

Standards

| | |
|---------------------------------------|---|
| Certifications | UL 61010-1 3rd edition, CAN/CSA-C22.2 No.61010-1 3rd. edition 2012-05 |
| Electrical safety, Maximum height (m) | 2000 |
| Standards | IEC 61010-1 (1rd. Edition), UNE-EN 61000-6-2, UNE-EN 61000-6-4, IEC 60664-1, IEC 61010-2-030 (First Edition). |

Voltage measurement circuit

| | |
|-----------------|-----|
| Input impedance | 3kΩ |
|-----------------|-----|

Digital inputs

| | |
|-------------------------|------------------------|
| Input/output insulation | 4 kV |
| Quantity | 8 |
| Type | Potential-free contact |

Digital transistor outputs

| | |
|--|-----------------|
| Pulse width | 1 ms |
| Quantity | 8 |
| Type | NPN |
| Pulse output, time period (Ton / Toff) | 0,3 ms / 0,7 ms |
| Maximum frequency | 1 kHz |
| Maximum current | 130 mA |
| Maximum voltage | 48 Vdc |



M-CVM-AB-8I-80TR

Expansion modules M-CVM-AB-8I-80TR

Code: M56E01.

M-CVM-AB-8I-80TR
Expansion modules

| CODE | TYPE | Transistor output | Digital inputs |
|---------|------------------|-------------------|----------------|
| M56E01. | M-CVM-AB-8I-80TR | 8 | 8 |



M-CVM-AB-8I-80TR

Expansion modules M-CVM-AB-8I-80TR

Code: M56E01.

Dimensions



Connections

