

## TP-88 400 /5A

TP-88 400 /5A, Split core current transformers

Code: M70133.

- > Flat strip(mm): 80 x 80
- > System: Single-phase
- > Class 0,5 Power (VA): 1,5
- > Class 1 Power (VA): 3
- > Class 3 Power (VA): 10
- > Measurement Range (A): 400/5
- > Input current: 400 A
- > Transformer type: Split core


### Description

Open-core transformers that can measure current without having to interrupt the electric supply. In other words, the installation does not have to be dismantled in order to install them.

- Range: 100 to 5000 A
- Busbar dimensions: 20 x 30 mm to 80 x 160 mm
- The transformer certificate is attached.

### Application

Converting a high nominal current to a lower current so that it can be measured by the unit. They have a split core and can be installed with no need to interrupt the installation's power supply.



# TP-88 400 / 5A

Split-core measurement current transformer

Code: M70133.

## Specifications

### Electrical characteristics

Safety factor (SF)	FS 10
Power	3 VA (Class 1)

### Mechanical characteristics

Size (mm) width x height x depth	145 x 144 x 50 (mm)
Weight (kg)	0,959

### Environmental characteristics

Thermal Class	Class B (+130 °C)
Working temperature	-5 ... 40 °C

### Specific technical characteristics of current sensors

Operating voltage	0,72 kV~ max.
-------------------	---------------


### Current measurement circuit

Primary current measurement	400 A
Dynamic current (Idyn)	2,5 Ith
Thermal short-circuit current (Ith)	60 In
Transformation ratio	... / 5 A

### Standards

Standards	IEC 44-1, UNE 21 088-1, UL 94, VDE 0414
-----------	---

For other configurations see table of additional features



## TP-88 400 / 5A

Split-core measurement current transformer

Code: M70133.

## Dimensions

