



TP-816 1250/5

TP-816 1250/5, Split core current transformers

Code: M7015A.

- > Flat strip(mm): 80 x 160
- > System: Single-phase
- > Class 0,5 Power (VA): 8
- > Measurement Range (A): 1250/5
- > Input current: 1250 A
- > Transformer type: Split core

Description

Open-core transformers that can measure current without having to interrupt the electric supply. In other words, the installation does not have to be dismantled in order to install them.

- Range: 100 to 5000 A
- Busbar dimensions: 20 x 30 mm to 80 x 160 mm
- The transformer certificate is attached.

Application

Converting a high nominal current to a lower current so that it can be measured by the unit. They have a split core and can be installed with no need to interrupt the installation's power supply.



TP-816 1250/5

Split-core measurement current transformer

Code: M7015A.

Specifications

Electrical characteristics

Safety factor (SF)	FS 10
Power	8 VA (Class 0,5)

Mechanical characteristics

Size (mm) width x height x depth	245 x 184 x 70 (mm)
Weight (kg)	2,582

Environmental characteristics

Thermal Class	Class B (+130 °C)
Working temperature	-5 ... 40 °C

Specific technical characteristics of current sensors

Operating voltage	0,72 kV~ max.
-------------------	---------------

Current measurement circuit

Primary current measurement	1250 A
Dynamic current (Idyn)	2,5 Ith
Thermal short-circuit current (Ith)	60 In
Transformation ratio	... / 5 A

Standards

Standards	IEC 44-1, UNE 21 088-1, UL 94, VDE 0414
-----------	---

For other configurations see table of additional features



TP-816 1250/5

Split-core measurement current transformer

Code: M7015A.

Dimensions

