

STQ-24 250/250 mA, Split core current transformer

Code: M7371900A0000

- > System: Single-phase
- > Class 1 Power (VA): 0,1
- > Measurement Range (A): 250/250 mA
- > Input current: 250 A
- > Transformer type: Split core

#### Description

Open-core current transformers with compact dimensions for easy installation. This type of transformer is very easy to install and uninstall on compact panels where the reduced space makes it difficult to take current measurements. In addition, their open-core design means that they can take measurements without having to interrupt the electric supply. The primary current measurement range is from 100 A to 300 A using different secondary outputs (.../1A, .../5A or .../250mA) with a maximum admissible cable diameter of 24 mm.

#### Application

Quick and easy assembly are a fundamental aspect when taking temporary measurements in an electrical installation. **STQ-24** transformers can take energy measurements together with **CIRCUTOR**'s power analyzers or energy meters (**CVM-MINI, CVM-NET, CVM-C, CVM-B, EDMk**, etc.) without having to interrupt the electric supply. The open-core design of the transformer makes it very easy to install and allows installers to take electrical measurements in less time.

Circutor



Split-core current Transformers

Code: M7371900A0000

#### Specifications

Safety factor (SF)	5
Power	0.1 VA (class 1)
Insulation voltage between terminals S1-S2	3 kV
lechanical characteristics	
Size (mm) width x height x depth	53 x 70 x 43.2 (mm)
Envelope	PC LexanTM 940-701
Weight (kg)	0,2
nvironmental characteristics	
Thermal Class	Class B (+130 °C)
Protection class	IP 20
Relative humidity (without condensation)	15 85%
Storage temperature	-20 75 °C
Working temperature	-5 +40 °C
pecific technical characteristics of current sensors	
Inner diameter Ø (mm)	24
Operating voltage	0,72 kV~ máx.
urrent measurement circuit	
urrent measurement circuit Nominal frequency	50 / 60 Hz
	50 / 60 Hz 250 A
Nominal frequency	
Nominal frequency Primary current measurement	250 A
Nominal frequency Primary current measurement Allowable overload	250 A 1,2 In
Nominal frequency Primary current measurement Allowable overload Dynamic current (Idyn)	250 A 1,2 In 2,5 Ith
Nominal frequency Primary current measurement Allowable overload Dynamic current (ldyn) Thermal short-circuit current (lth)	250 A 1,2 In 2,5 Ith 60 In
Nominal frequency Primary current measurement Allowable overload Dynamic current (Idyn) Thermal short-circuit current (Ith) Transformation ratio	250 A 1,2 In 2,5 Ith 60 In
Nominal frequency Primary current measurement Allowable overload Dynamic current (Idyn) Thermal short-circuit current (Ith) Transformation ratio	250 A 1,2 In 2,5 Ith 60 In / 250 mA
Nominal frequency Primary current measurement Allowable overload Dynamic current (Idyn) Thermal short-circuit current (Ith) Transformation ratio tandards Electrical safety, Maximum height (m)	250 A 1,2 In 2,5 Ith 60 In / 250 mA 1000

**STQ** Current transformers, split core

Circutor



Split-core current Transformers

#### Code: M7371900A0000

CODE	ТҮРЕ	Measurement Range (A)	Class 1 Power (VA)	Class 3 Power (VA)
5A				
M73715.	STQ-24 100/5A	100/5	_	1
M73717.	STQ-24 150/5A	150/5	-	1
M73718.	STQ-24 200/5A	200/5	-	1
M73719.	STQ-24 250/5A	250/5	1	-
M7371A.	STQ-24 300/5A	300/5	1	_
1A				
M737150010000	STQ-24 100/1A	100/1	_	1
M737170010000	STQ-24 150/1A	150/1	_	1
M737180010000	STQ-24 200/1A	200/1	-	1
M737190010000	STQ-24 250/1A	250/1	1	-
M7371A0010000	STQ-24 300/1A	300/1	1	-
250mA				
M7371200A0000	STQ-24 50/250 mA	50/250 mA	-	0,1
M7371500A0000	STQ-24 100/250 mA	100/250 mA	-	0,1
M7371700A0000	STQ-24 150/250 mA	150/250 mA	-	0,1
M7371800A0000	STQ-24 200/250 mA	200/250 mA	-	0,1
M7371900A0000	STQ-24 250/250 mA	250/250 mA	0,1	-
M7371A00A0000	STQ-24 300/250 mA	300/250 mA	0,1	-

Circutor



Split-core current Transformers

Code: M7371900A0000

# Dimensions

# Connections

×

×

