

MYeBOX-1500, Portable power analyzer with recording of quality events and transients

Code: M840330000A00 DESCATALOGADO

- > Communications: Wi-Fi | 3G
- > Transistor output: 2
- > Digital inputs: 2
- > No. of voltage measurement inputs: 5
- > Measuring current Channels: 5
- > Class: Class A

Description

MYeBOX® is a range of portable analysers that can be configured from an app and/or a website to analyse and record electrical parameters, measure and record waveform transients and network quality parameters, as per the EN 50160 standard. The information is accessible remotely from the app and/or website. MYeBOX® measures and records electrical parameters in single-phase, two-phase or three-phase installations (with and without a neutral).

The app/website is connected to the device to display the measured data in real time, fully configure the device, start or stop the data recording, send the recorded data to the **MYeBOX®** Cloud platform, and even access the data from the memory to view it graphically or in table form. The remote connectivity lets you analyse the measured data from anywhere. The recorded data can also be sent to a data repository for further analysis in PowerVision Plus. The device can be configured locally using the capacitive keyboard and the on-screen menu options.

MYeBOX® 150 and MYeBOX® 1500 have the following features and functions:

- \circ 4 voltage measurement inputs (U_1 , U_2 , U_3 , U_n)
- \circ 4 current measurement inputs (I_1 , I_2 , I_3 , I_n)
- Measurement of the main electrical parameters
- Measurement of network quality parameters
- True RMS measurement (TRMS)
- Measurement of consumption and generation (4Q)
- Voltage quality event log, according to EN 61000-4-30
- Transients log
- Recording of the wave shape associated with the quality events and transients
- Measurement according to EN 61000-4-30
- Power supply is independent of the measurement
- Recording of the wave shape for each recording period
- LCD Screen
- Capacitive keypad
- Micro-USB port to download data
- Automatic detection of clamps
- Identification of phases with colours
- Compatible with clamps with EEPROM
- Recording of system events (EVA)
- NTP synchronisation
- Sending of alarms via e-mail
- Wi-Fi communications (access point/terminal)

The MYeBOX® 1500 model also has:



Portable power analyzer

Code: M840330000A00

- \circ 1 voltage measurement input $U_{
 m ref}$
- 1 leakage current measurement input
- $\,\circ\,$ 2 transistor inputs to centralise impulses / tariff / state
- 2 transistor outputs for alarms
- 3G/4G communications

Application

MYeBOX can be used to:

- $\circ~$ Prepare complete studies of an electrical installation.
- Analyse consumption, load curves, disturbances in the installation's voltage, display wave shapes, harmonics study or flicker measurement, among other options.
- Perform audits and analyses remotely.

Page 3 of 7



MYeBOX-1500

Portable power analyzer

Code: M840330000A00

Specifications

Autonomy	2 h (without 3G), 50 min (with 3G)
Battery type	Litio (3,7 Vc.c.)
Capacity	3700 mAh
Load temperature	0 40 °C
Load time	6 h
AC power supply	
Installation category	CAT II 300 V
Consumption	2228 VA
Frequency	4763 Hz
Nominal voltage	100240 Vc.a.(Adaptador de alimentación de c.a.)
Powered by charger, adapter	
Output voltage	9 Vc.c.
Maximum power	20 W
Battery specification	
Capacity	220 mAh
Performance-guarantee	10 años
Туре	Litio
Voltage	3 Vc.c.
Standards	
Certifications	CE
Electrical safety, Maximum height (m)	2000
Standards	Recycling European Directive 2002/96/EC, EN 61326-1, IEC 61010-1, 3rd Editio
Current measurement circuit	
Installation category	CAT III 600 V
Nominal current (In)	Depending on the clamp
Phase current measurement	Transformadores con salida 0,250 A ó 0,333 V
Phase current measuring range	1200 % In
Maximum input current consumption	0,0004 VA
Maximum pulse current	3 x In A
Minimum current measurement	Depending on the clamp
/oltage measurement circuit	
Installation category	CAT III 600 V

Page 4 of 7



MYeBOX-1500

Portable power analyzer

Code: M840330000A00

Sampling frequency4565 HzInput impedance2,4 MΩFrequency measuring range42,569 HzVoltage measuring range10 600 V~ (Ph-N)Minimum measurement voltage (Vstart)10 V acInsulationDouble-insulated electric shock protection class II (IEC 61010-1)InsulationInput/output insulation2,7 kVQuantity2TypePotential-free contactMaximum short-circuit current5 mAMaximum open circuit voltage49 Vdc	Consumption	0,15 VA																																																															
input impedance24 M0Frequency messuring range42.5 69 HzVoltage measuring range0 60 Vr. (Ph. N)Minimum messurement voltage (Vstart)10 V acInsultationDouble-insulated electric shock protection dass II (EC 61010-1)InsultationDouble-insulated electric shock protection dass II (EC 61010-1)Ingut/output insulation2,7 V/Quentity2TypeOktenti-free contactMaximum open circuit voltage5 mAMaximum open circuit voltage4 VolcaIngut foutput5 mAMaximum open circuit voltage1 Sin, Sin, Sin, Sin, Sin, Sin, Sin, Sin,																																																																	
Prequency measuring range42.569 lf2Voltage measuring range1060 V- (Ph-N)Minimum measurement voltage (Vstart)10 V ocInstantionDouble-insulated electric shock protection dass II (EC 6010-1)InstantionDouble-insulated electric shock protection dass II (EC 6010-1)InstantionDouble-insulated electric shock protection dass II (EC 6010-1)Instantion27 KVQuantity2QuantityS nAMaximum short-circuit current5 nAMaximum open circuit voltage49 VaCPresenceStatistic outputMustimum open circuit voltage19 No. 50, 10, 10TypeDolt SetTQuantity2Quantity2Quantity2Quantity2Maximum soltage90 mAMaximum outpage90 mAMaximum outpage90 mAMaximum outpage38 (EC 61000-4-30)Maximum outpage0as A (EC 61000-4-30)Voltage unbalance (Kol)Cass A (EC 61000-4-30)Voltage unbalance (Kol)Cass A (EC 61000-4-30)Voltage unbalance (Kol)Cass A (EC 61000-4-30)PhaseurementCass A (EC 61000-4-30)Phaseurement (Kował)Cass A (EC 61000-4-30)Phaseurement (Kował)		2,4 ΜΩ																																																															
Witage measuring range10 600 V- (Ph-N)Minnum messurement voltage (Vstart)10 V acinstalationDouble-insulated electric stock protection class II (EC 61010-1)instalationDouble-insulated electric stock protection class II (EC 61010-1)instalation2 / KVinstalation2 / KVquantity2TypePotential-rescontactMaximum open circul voltage4 9 Vdcinstance open circul voltage4 9 Vdcinstance open circul voltage5 7 KVQuantity2TypeObtom Circul voltageWate timeIn, 5m, 15m, 1h, 1dTypeOpto MOSFETQuantity2Quantity2Quantity2Quantity3.1Rescence2Instance2Quantity2Quantity2Quantity2Quantity3.1Quantity <td></td> <td>42,5 69 Hz</td>		42,5 69 Hz																																																															
Mininum measurement voltage (vtart)10 V acInctrical safelyInsulationDouble-insulated electric shock protection class II (EC 61010-1)Inglat inpus2Input/ output insulation2,7 kVQuantity2TypePotential-Free contactMaximum open circuit voltage4,9 vdcInput/ output insulation2,7 kVMaximum open circuit voltage5 mAMaximum open circuit voltage5 mAInput/ output2,0 vdcInput outputs2,0 vdc		10 600 V~ (Ph-N)																																																															
Incluicion Double-insulated electric shock protection class II (EC 61010-1) inplationut Double-insulated electric shock protection class II (EC 61010-1) inplationut 27 kV Quanthy 2 NV Quanthy 2 Notental-free contact Maximum short-circuit current 5 mA Inple Far Star Star Component Inple Far Star Star Component Inple Doub MSFET Maximum voltage 2 Maximum voltage 3 NA Maximum voltage 3 NA Maximum voltage 3 Star CE 60000-4-301 Maximum voltage Gass Al (EC 6000-4-30) Maximum		10 V ac																																																															
Insulation Double-insulated electric shock protection class II (IEC 61010-1) light lights Imply four protection class II (IEC 61010-1) light lights 2 Imply four put insulation 2,7 kV Quantity 2 Type Potential-free contact Maximum short-circuit current 5 mA Maximum open circuit voltage 49 Vdc Maximum open circuit voltage 5 mA Maximum open circuit voltage 5 mA Maximum open circuit voltage 49 Vdc Maximum open circuit voltage 5 mA Quantity 7 gen Opto MOSFET 7 gen Maximum current 90 mA Maximum voltage 48 Vcc. Maximum voltage 3,1 Maximum voltage 2as A (IEC 61000-4-30) Voltage unsymmetry (Ka) Class A (IEC 61000-4-30) Voltage unsymmetry (Ka) Class A (IEC 61000-4-30) Voltage unsalence (Kd) Class A (IEC 61000-4-30) Voltage unsalence (Kd) Class A (IEC 61000-4-30) Voltage unsalence (Kd) Class A (IEC 61000-4-30)																																																																	
igital inputsinputs27 kVQuantity2Quantity2TypePetential-free contactMaximum short-circuit current5 mAMaximum open circuit voltage																																																																	
Input/output insulation2.7 kVQuantity2TypePotential-free contactTypePotential-free contactMaximum short-circuit current5 mAMaximum open circuit voltage49 VdctemorytemoryWrite time1s, tm, Sm, 15m, 1h, 1dTypeFAT 32Jajala transistor outputs2Maximum current0 pot MOSFETMaximum voltage48 Vcc.Ketanical characteristics90 nAWeight (kg)3,1Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurement (kor/h)Class A (IEC 61000-4-30)Rective energy measurement (kor/h)Class I 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kor/h)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Insulation	Double-insulated electric shock protection class II (IEC 61010-1)																																																															
Quantity2TypePolential-free contactMaximum short-circuit current5 mAMaximum open circuit voltage4.9 VdcMaximum open circuit voltage1.9 VdcMartentime1.8 Inn, 51m, 1h, 1dMarte time1.8 Inn, 51m, 1h, 1dTypePAT 32Mathetime2Maximum current90 MdoSFETMaximum voltage90 MdoSFETMaximum voltage90 MdoSFETMaximum voltage3.1Maximum voltage3.1Adatasenteristics1.9 MainteristicsCurrent asymmetry (Ka)Gasa A (EC 61000-4-30)Voltage asymmetry (Ka)Gasa A (EC 61000-4-30)Voltage unbalance (Kd)Gasa A (EC 61000-4-30)Phase current measurementGasa A (EC 61000-4-30)Phase current measurementGasa (A (EC 61000-4-30))Phase current measurement (kvar)Gasa (A (EC 61000-4-30))Rective power measurement (kvar)Gasa (1.2 Mainteristics)Rective power measurement (kvar)Gasa (1.2 Mainteristics)Apprent power measurement (kvar)Gasa (1.2 Mainteristics) <td>igital inputs</td> <td></td>	igital inputs																																																																
TypePotential-free contactMaximum short-circuit vortage5 mAMaximum open circuit voltage49 Vdctenory5 mAWrite time15,1m, 5m, 15m, 1h, 1dTypeFAT 32igital transistor outpots2Quantity2Type0 th MOSFETMaximum voltage90 mAMaximum voltage90 mAiethenical characteristics2Verify time3,1Everify time3,1Voltage asymmetry (Ka)0 cas A (IEC 6100-4-30)Voltage asymmetry (Ka)0 cass A (IEC 6100-4-30)Voltage unbalance (Kd)0 cass A (IEC 6100-4-30)Prequent measurement0 cass A (IEC 6100-4-30)Prequent measurement (kvarh)0 cas	Input/output insulation	2,7 kV																																																															
NMaximum short-circuit current5 mAMaximum open circuit voltage49 VdcMaximum open circuit voltage15, 1m, 5m, 1m, 1m, 1mWrite time15, 1m, 5m, 1m, 1mTypeFAT 32igital transistor outputs2Quantity2Type0pto MOSFETMaximum current90 mAMaximum voltage48 Vc.CIdentify3.1Identify1Current asymmetry (Ka)Class A (IEC 1000-4-30)Voltage asymmetry (Ka)Class A (IEC 1000-4-30)Voltage unbalance (Kd)Class A (IEC 1000-4-30)Frequency measurement (kvarh)Class 1.2.00 % in (IEC 61557-12) (Vn ac 230/110)Apprent power measurement (kvark)Class 1.1 digit (IEC 61557-12) (Vn ac 230/110)	Quantity	2																																																															
Maximum open circuit voltage49 VdcMaximum open circuit voltage	Туре	Potential-free contact																																																															
Instrumentation Instrumentation is, ins, ins, ins, ins, ins, ins, ins, i	Maximum short-circuit current	5 mA																																																															
Write time1s, 1m, 5m, 15m, 1h, 1dTypeFAT 32Injtalt transistor outputs2Quantity2TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.technnical characteristicsWeight (kg)3,1Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Voltage unbalance (kd)Class A (IEC 61000-4-30)Phase current measurementClass A (2.569 H2) (IEC 61000-4-30)Phase current measurement (kvarh)Class 1 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 1 1 digit (IEC 61557-12) (Vn ac 230/110)	Maximum open circuit voltage	49 Vdc																																																															
TypeFAT 32Igital transitor outputsQuantity2TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc. Ctechenical characteristicstechenical characteristicsVerget colspan="2">Colspan="2"Colspan="2"Colspan="2"Colspan="2"Colspan="2"Colspan="2"Colspan="2"Colspan="2"Colspan="2" <tr <td="" cols<="" td=""><td>1emory</td><td></td></tr> <tr><td>Appendix igital transistor outputs Quantity 2 Type Opto MOSFET Maximum current 90 mA Maximum voltage 48 Vc. International characteristics </td><td>Write time</td><td>1s, 1m, 5m, 15m, 1h, 1d</td></tr> <tr><td>Initial transistor outputsQuantity2TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.technical characteristicstechnical characteristics<t< td=""><td>Туре</td><td>FAT 32</td></t<></td></tr> <tr><td>Quantity2QuantityQto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.Atechanical characteristicsWeight (kg)3,1Ausimum voltageSa A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Phase current measurement (kvarh)Class A (IEC 61000-4-30)Reactive power measurement (kvarh)Class A (IEC 61000-4-30)Apparent power measurement (kvarh)Class 1 1 digit (IEC 61557-12) (vn ac 230/110)</td><td></td><td></td></tr> <tr><td>TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.Adexincial characteristics3,1Aresurement accuracyClass A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Phase current measurement (kvarh)Class A (IEC 61000-4-30)Reactive power measurement (kvarh)Class 1 (IEC 61000-4-30)Reactive power measurement (kvarh)Class 1 (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)Class 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>Digital transistor outputs</td><td></td></tr> <tr><td>Maximum current90 mAMaximum voltage90 mAMaximum voltage48 Vc.dechanical characteristicsWeight (kg)3,1Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kVA)Class 1 ± digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>Quantity</td><td></td></tr> <tr><td>Maximum voltage48 Vc.c.Maximum voltage48 Vc.c.Mechanical characteristicsWeight (kg)3,1Current accuracyClass A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvarh)Class 1 (IEC 62053-23)Apparent power measurement (kVA)Class 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>Туре</td><td>Opto MOSFET</td></tr> <tr><td>Accession of the second of</td><td>Maximum current</td><td>90 mA</td></tr> <tr><td>Weight (kg)3,1tessurement accuracyCurrent asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (25 69 Hz) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kVA)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Appenent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>Maximum voltage</td><td>48 Vc.c.</td></tr> <tr><td>AdvanceAdvanceAdvanceAdvanceAdvanceCurrent asymmetry (Ka)Current unbalance (Kd)Current unbalance (Kd)Current unbalance (Kd)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass 0,2 (1200 % In) (IEC 61557-12)Reactive energy measurement (kvarh)Reactive power measurement (kvark)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)</td><td>fechanical characteristics</td><td></td></tr> <tr><td>Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementclass 0,2 (1200 % ln) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>Weight (kg)</td><td>3,1</td></tr> <tr><td>Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementclass 0,2 (1200 % ln) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>leasurement accuracy</td><td></td></tr> <tr><td>Voltage asymmetry (Ka) Class A (IEC 61000-4-30) Current unbalance (Kd) Class A (IEC 61000-4-30) Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (IEC 61000-4-30) Phase current measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td>Class A (IEC 61000-4-30)</td></tr> <tr><td>Current unbalance (Kd) Class A (IEC 61000-4-30) Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % ln) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td></td></tr> <tr><td>Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % ln) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kVAr) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td></td></tr> <tr><td>Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % In) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td></td></tr> <tr><td>Phase current measurementclass 0,2 (1200 % ln) (IEC 61557-12)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td>Class A (42.5 69 Hz) (IEC 61000-4-30)</td></tr> <tr><td>Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td>Phase current measurement</td><td></td></tr> <tr><td>Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td></td></tr> <tr><td>Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)</td><td></td><td></td></tr> <tr><td></td><td></td><td></td></tr> <tr><td></td><td></td><td></td></tr>	1emory		Appendix igital transistor outputs Quantity 2 Type Opto MOSFET Maximum current 90 mA Maximum voltage 48 Vc. International characteristics	Write time	1s, 1m, 5m, 15m, 1h, 1d	Initial transistor outputsQuantity2TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.technical characteristicstechnical characteristics <t< td=""><td>Туре</td><td>FAT 32</td></t<>	Туре	FAT 32	Quantity2QuantityQto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.Atechanical characteristicsWeight (kg)3,1Ausimum voltageSa A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Phase current measurement (kvarh)Class A (IEC 61000-4-30)Reactive power measurement (kvarh)Class A (IEC 61000-4-30)Apparent power measurement (kvarh)Class 1 1 digit (IEC 61557-12) (vn ac 230/110)			TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.Adexincial characteristics3,1Aresurement accuracyClass A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Phase current measurement (kvarh)Class A (IEC 61000-4-30)Reactive power measurement (kvarh)Class 1 (IEC 61000-4-30)Reactive power measurement (kvarh)Class 1 (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)Class 1 digit (IEC 61557-12) (Vn ac 230/110)	Digital transistor outputs		Maximum current90 mAMaximum voltage90 mAMaximum voltage48 Vc.dechanical characteristicsWeight (kg)3,1Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kVA)Class 1 ± digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Quantity		Maximum voltage48 Vc.c.Maximum voltage48 Vc.c.Mechanical characteristicsWeight (kg)3,1Current accuracyClass A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvarh)Class 1 (IEC 62053-23)Apparent power measurement (kVA)Class 1 digit (IEC 61557-12) (Vn ac 230/110)	Туре	Opto MOSFET	Accession of the second of	Maximum current	90 mA	Weight (kg)3,1tessurement accuracyCurrent asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (25 69 Hz) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kVA)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Appenent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Maximum voltage	48 Vc.c.	AdvanceAdvanceAdvanceAdvanceAdvanceCurrent asymmetry (Ka)Current unbalance (Kd)Current unbalance (Kd)Current unbalance (Kd)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass 0,2 (1200 % In) (IEC 61557-12)Reactive energy measurement (kvarh)Reactive power measurement (kvark)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)	fechanical characteristics		Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementclass 0,2 (1200 % ln) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Weight (kg)	3,1	Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementclass 0,2 (1200 % ln) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	leasurement accuracy		Voltage asymmetry (Ka) Class A (IEC 61000-4-30) Current unbalance (Kd) Class A (IEC 61000-4-30) Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (IEC 61000-4-30) Phase current measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)		Class A (IEC 61000-4-30)	Current unbalance (Kd) Class A (IEC 61000-4-30) Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % ln) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)			Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % ln) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kVAr) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)			Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % In) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)			Phase current measurementclass 0,2 (1200 % ln) (IEC 61557-12)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)		Class A (42.5 69 Hz) (IEC 61000-4-30)	Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Phase current measurement		Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)			Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)								
1emory																																																																	
Appendix igital transistor outputs Quantity 2 Type Opto MOSFET Maximum current 90 mA Maximum voltage 48 Vc. International characteristics	Write time	1s, 1m, 5m, 15m, 1h, 1d																																																															
Initial transistor outputsQuantity2TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.technical characteristicstechnical characteristics <t< td=""><td>Туре</td><td>FAT 32</td></t<>	Туре	FAT 32																																																															
Quantity2QuantityQto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.Atechanical characteristicsWeight (kg)3,1Ausimum voltageSa A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Phase current measurement (kvarh)Class A (IEC 61000-4-30)Reactive power measurement (kvarh)Class A (IEC 61000-4-30)Apparent power measurement (kvarh)Class 1 1 digit (IEC 61557-12) (vn ac 230/110)																																																																	
TypeOpto MOSFETMaximum current90 mAMaximum voltage48 Vc.c.Adexincial characteristics3,1Aresurement accuracyClass A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Phase current measurement (kvarh)Class A (IEC 61000-4-30)Reactive power measurement (kvarh)Class 1 (IEC 61000-4-30)Reactive power measurement (kvarh)Class 1 (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)Class 1 digit (IEC 61557-12) (Vn ac 230/110)	Digital transistor outputs																																																																
Maximum current90 mAMaximum voltage90 mAMaximum voltage48 Vc.dechanical characteristicsWeight (kg)3,1Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kVA)Class 1 ± digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Quantity																																																																
Maximum voltage48 Vc.c.Maximum voltage48 Vc.c.Mechanical characteristicsWeight (kg)3,1Current accuracyClass A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvarh)Class 1 (IEC 62053-23)Apparent power measurement (kVA)Class 1 digit (IEC 61557-12) (Vn ac 230/110)	Туре	Opto MOSFET																																																															
Accession of the second of	Maximum current	90 mA																																																															
Weight (kg)3,1tessurement accuracyCurrent asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass A (25 69 Hz) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kVA)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Appenent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Maximum voltage	48 Vc.c.																																																															
AdvanceAdvanceAdvanceAdvanceAdvanceCurrent asymmetry (Ka)Current unbalance (Kd)Current unbalance (Kd)Current unbalance (Kd)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementClass 0,2 (1200 % In) (IEC 61557-12)Reactive energy measurement (kvarh)Reactive power measurement (kvark)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)	fechanical characteristics																																																																
Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementclass 0,2 (1200 % ln) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Weight (kg)	3,1																																																															
Current asymmetry (Ka)Class A (IEC 61000-4-30)Voltage asymmetry (Ka)Class A (IEC 61000-4-30)Current unbalance (Kd)Class A (IEC 61000-4-30)Voltage unbalance (Kd)Class A (IEC 61000-4-30)Frequency measurementClass A (IEC 61000-4-30)Phase current measurementclass 0,2 (1200 % ln) (IEC 61000-4-30)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	leasurement accuracy																																																																
Voltage asymmetry (Ka) Class A (IEC 61000-4-30) Current unbalance (Kd) Class A (IEC 61000-4-30) Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (IEC 61000-4-30) Phase current measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)		Class A (IEC 61000-4-30)																																																															
Current unbalance (Kd) Class A (IEC 61000-4-30) Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % ln) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)																																																																	
Voltage unbalance (Kd) Class A (IEC 61000-4-30) Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % ln) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kVAr) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)																																																																	
Frequency measurement Class A (42.5 69 Hz) (IEC 61000-4-30) Phase current measurement class 0,2 (1200 % In) (IEC 61557-12) Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)																																																																	
Phase current measurementclass 0,2 (1200 % ln) (IEC 61557-12)Reactive energy measurement (kvarh)Class 1 (IEC 62053-23)Reactive power measurement (kvar)Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110)Apparent power measurement (kVA)class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)		Class A (42.5 69 Hz) (IEC 61000-4-30)																																																															
Reactive energy measurement (kvarh) Class 1 (IEC 62053-23) Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)	Phase current measurement																																																																
Reactive power measurement (kvar) Class 1 ± 1 digit (IEC 61557-12) (Vn ac 230/110) Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)																																																																	
Apparent power measurement (kVA) class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)																																																																	



Portable power analyzer

Code: M840330000A00

Active power measurement (kW)	class 0,5 ± 1 digit (IEC 61557-12) (Vn ac 230/110)
Power factor measurement	Class 0.5 (IEC 61557-12)
Voltage THD	Class 0.5 (IEC 61557-12)
Phase voltage measurement	Class 0,2 (10600 VPh-N ~) (IEC 61557-12)
Pinst. Flicker	3 % (IEC 61000-4-15)
Pst Flicker	5 % (0,2 10Pst) (IEC 61000-4-15)
Current harmonics (THD)	(up 50th) Class 1 (IEC 61000-4-7)
Voltage harmonics (THD)	(up 50th) Class 1 (IEC 61000-4-7)
Radio communication	
Band	UMTS/HSPA: 850/900/1900/2100 MHz. # GSM /GPRS /EDGE: 850/900/1800/1900 MHz.
Technology / Type	3G
Wireless communication	
Band	2,4 GHz.
Technology / Type	Wi-Fi

MYeBOX

Portable power analyzer with recording of quality events and transients

CODE	ТҮРЕ	Class	Communications	No. of voltage measurement inputs	Measuring current Channels	Measuring Channels	Transistor output	Digital inputs	Nr Sensors
M840230000A00	MYeBOX-150	Class A	Wi-Fi	4	4				
Portable analyzer l	kits with current sensors								
M844330000A00	MYeBOX-1500-4G		Wi-Fi 4G			5	2	2	
M8445B0000A00	MYeBOX-1500-4G + 3 FLEX-R45		Wi-Fi 4G			5	2	2	3 FLEX-R45
M8445C0000A00	MYeBOX-1500-4G + 4 FLEX-R45		Wi-Fi 4G			5	2	2	4 FLEX-R45
M8445D0000A00	MYeBOX-1500-4G + 3 FLEX-R80		Wi-Fi 4G			5	2	2	3 FLEX-R80
M8445E0000A00	MYeBOX-1500-4G + 4 FLEX-R80		Wi-Fi 4G			5	2	2	4 FLEX-R80
M844530000A00	MYeBOX-1500-4G + 3 CPG-100		Wi-Fi 4G			5	2	2	3 CPG-100
M844550000A00	MYeBOX-1500-4G + 3 CPRG-500		Wi-Fi 4G			5	2	2	3 CPRG-500
M84023.	MYeBOX-150	According to Class A	Wi-Fi	4	4				
M84433.	MYeBOX-1500-4G		Wi-Fi 4G			5	2	2	
M8404B.	MYeBOX-150+3 FLEX-R45	According to Class A	Wi-Fi	4	4				3 FLEX-R45
M8445B.	MYeBOX-1500-4G + 3 FLEX-R45		Wi-Fi 4G			5	2	2	3 FLEX-R45
M8404C.	MYeBOX-150-4 FLEX-R45	According to Class A	Wi-Fi	4	4				4 FLEX-R45
M8445C.	MYeBOX-1500-4G + 4 FLEX-R45		Wi-Fi 4G			5	2	2	4 FLEX-R45



Portable power analyzer

Code: M840330000A00

CODE	ТҮРЕ	Class	Communications	No. of voltage measurement inputs	Measuring current Channels	Measuring Channels	Transistor output	Digital inputs	Nr Sensors
M8404D.	MYeBOX-150-3 FLEX-R80	According to Class A	Wi-Fi	4	4				3 FLEX-R80
M8404E.	MYeBOX-150-4 FLEX-R80	According to Class A	Wi-Fi	4	4				4 FLEX-R80
M8445E.	MYeBOX-1500-4G + 4 FLEX-R80		Wi-Fi 4G			5	2	2	4 FLEX-R80
M84043.	MYeBOX-150 + 3 CPG-100	According to Class A	Wi-Fi	4	4				3 CPG-100
M84453.	MYeBOX-1500-4G + 3 CPG-100		Wi-Fi 4G			5	2	2	3 CPG-100
M84045.	MYeBOX-150 + 3 CPRG-500	According to Class A	Wi-Fi	4	4				3 CPRG-500
M84455.	MYeBOX-1500-4G + 3 CPRG-500		Wi-Fi 4G			5	2	2	3 CPRG-500

Analyser with built-in SD memory and Cloud Includes voltage cables, alligator clips, USB cable, fastening strap, magnetic support, battery, power supply and carrying bag. Please contact us for other clamp or clamp length combinations



Portable power analyzer

Code: M840330000A00

Dimensions

Connections

×

×

