



CBS-1600A, Multi-channel leakage current monitoring relay type A

Code: P12B01.

> Protocol: Modbus/RTU

> Módules: 6

> Pre-alarm relay: Yes

> Communications: RS-485

> N° relays: 2

> N<sup>a</sup> Input channels: 16 (A)

> Power supply: 230 V  $\sim$  ( $\pm$  15%)

> Delay: 0,1-0,3-0,5-0,8-1-2-3-5 s

> Sensitivity: 30 ... 3000 mA

> Mounting: DIN rail

#### Description

The CBS-1600A is an earth leakage current monitoring device that can be used to connect up to 16 type-A channels via transformers in the WGC range.

The device has a screen to display the 16 channels, 2 relays (alarm and pre-alarm) and RS-485 communications.

#### **Application**

The CBS-1600A is suitable for installations with all neutral regimes: TT, TN and IT, where residual current monitoring is required.







Type-A earth leakage monitoring relay with 16 channels

Code: P12B01.

### Specifications

AC power supply					
Installation category	CAT III 300V				
Consumption	10 VA				
Frequency	50 60 Hz				
Nominal voltage	230 V~ (± 15 %)				
Mechanical characteristics					
Size (mm) width x height x depth	105 x 117.85 x 74 (mm)				
Envelope	Self-extinguishing V0 plastic				
Fastening	DIN rail				
Weight (kg)	0,364				
Environmental characteristics					
Protection class	IP 30, IP 40 (Front) IK 08				
Relative humidity (without condensation)	5 95 %				
Storage temperature	-20 +70 °C				
Working temperature	-10 +50 °C				
Electrical characteristics					
Conditional short-circuit current (Icc)	Depends on the circuit breaker				
Sensor	Type A: WGC - WGS				
Туре	Туре А (50 60 Hz.)				
Digital inputs					
Input impedance	2 kΩ				
Input/output insulation	5.3 kV				
Туре	Potential-free contact				
Standards					
Electrical safety, Maximum height (m)	2000				
Electrical safety, Installation category	CAT III 300V ~				
Electrical safety, Contamination level/class	2				
Standards	IEC 62020-1				
User interface					
LED	2				
Keyboard	3 keys				
Display type	LCD (negative)				







Type-A earth leakage monitoring relay with 16 channels

Code: P12B01.

#### Digital relay outputs

2			
6 A			
230 V ~			
$60 \times 10^{3} (250 \text{ V} \sim / 5\text{A})$			
10 x 10 <sup>6</sup>			
1500 VA			
0.1-0.3-0.5-0.8-1-2-3-5 s			
Modbus/RTU			
RS-485			

#### CBS-1600A

16 channel differential current control unit type A

CODE	TYPE	N° relays	Nª Input channels	Communications	Protocol	Módules	Pre-alarm relay	Power supply
P12B01.	CBS-1600A	2	16 (A)	RS-485	Modbus/RTU	6	Yes	230 V ~ (± 15%)

Associated with WGC-type residual current transformers







Type-A earth leakage monitoring relay with 16 channels

Code: P12B01.

## **Dimensions**

# Connections





