



WRN-22-0,3

WRN-22-0,3

Code: P14212. **DESCATALOGADO**

- > Residual current relay
- > Usefull diam.(mm): 22
- > I Δ n (A): 0,3 A
- > Delay: 0,02 s

Description

- The **WRN-22** relay is an residual current relay with a built-in residual current transformer, with a diameter \varnothing 22 mm
- DIN 46277 Symmetrical profile coupling (EN 50022)
- The leakage is detected by means of sampling the residual current intensity and calculating its true root mean square (TRMS)
- Detection of the presence of voltage with LEDs
- TEST button.

Application

The WRN-22 residual current protection is a very interesting solution for small-scale installations with reduced space.



WRN-22-0,3

Residual current relay with built-in transformer.

Code: P14212.

Specifications

AC power supply

Frequency	50/60 Hz
Nominal voltage	230 V ~ ±20 %

Mechanical characteristics

Size (mm) width x height x depth	52.5 x 85 x 68 (mm)
Fastening	DIN rail
Weight (kg)	0,146

Environmental characteristics

Protection class	IP 20 (terminals), IP 41 (rear panel)
Working temperature	-10 ... +50 °C

Standards

Standards	IEC 1008, IEC 255-5, UNE 801-2, UNE 801-3, UNE 801-4, UNE 60730-1
-----------	---

Other digital relay outputs

Nominal current	3 A ~
-----------------	-------

Digital relay outputs

Contact-coil insulation	2000 Vca
-------------------------	----------

Differential protection

Type	Type A
Sensitivity ($I_{\Delta n}$), A	0,3
Delay time (t_{Δ})	0,02 s
Transformer	Internal

Thermal-magnetic protection

Nominal voltage	230 V ~
-----------------	---------

Protection

Measure	True root mean square (TRMS)
Circuit breaker type	Circuit breaker + trigger coil