Code:

Description

CIRCUTOR has a complete range of detuned reactors, p = 7%, with a resonance frequency of 189 Hz for 50 Hz networks (or, on demand, 227 Hz for 60 Hz networks). This is the most frequent tuning value to avoid any resonance with the 5th harmonic and over. The set of capacitors-reactors absorbs part of the current of the 5th harmonic and acts as a detuned filter for higher frequencies. In some installations, anyway, other value of p(%) can be required, for example, 8,7 % (170 Hz), 14 % (134 Hz).... **CIRCUTOR** can manufacture reactors adapted to any power, p(%), frequency, voltage (Un \leq 1000 VAC).

Reactors for low power rating, **RZ** range, are built with low losses magnetic sheets and coiled with aluminum wires. A terminal block for the connection of the reactor is fitted. Higher powers are covered by RBH range. These reactors are based on a magnetic sheet core with multiple air gaps, which provides them with excellent characteristics and low loss ratios.

Both **RZ** and **RBZ** reactors are subjected to a varnish vacuum impregnation, based on polyester resin, to increase the insulation, providing a greater mechanical resistance and reducing the level of noise.

Application

RZ and RBZ detuned reactors have been specially designed for their use in installations with capacitor banks with considerably high harmonic distortion rates. The reactors must be connected in series to the proper power capacitor for the satisfactory protection of the own capacitors and to avoid the resonance effects in the installation.

Circutor

Circutor



Code:

Specifications

50 Hz
1,17 x ln
1,75 x ln
2 In (1 min)
400 V,on request: up to 1000 V
±5%
4.07
3 kV
14 % (134 Hz)
250 x 245 x 145 (mm)
Conductor type: Aluminium strip / copper cable
21
class F (+155 °C) On request: class H (+180 °C)
IP 00
Inside
-10 +45 °C
UNE-EN 60289, IEC 60076
9125°C NC thermostat

RZ-RBZ

Reactors III for detuned filters

CODE	TYPE	L(mH)	For capacitor	In (A)	Frequency (Hz)	kvar (400 V)	Losses	Un (V)	Р%		
400 Vac, 50 Hz, f resonance = 189 Hz / p= 7%											
P73110.	RZ-5-400	7,66	CLZ-FP-46/6,25	7,2	50	5	26	400	7%		
P73112.	RZ-6,25-400	6,1	CLZ-FP-52/10	9	50	6,25	33	400	7%		





Code:

TYPE	L(mH)	For capacitor	In (A)	Frequency (Hz)	kvar (400 V)	Losses	Un (V)	P%
RZ-10-400	3,83	CLZ-FP-46/12,5	15	50	10	52	400	7%
RZ-12,5-400	3,05	CLZ-FP-46/15	18	50	12,5	57	400	7%
RZ-15-400	2,55	CLZ-FP-46/19	22	50	15	59	400	7%
RBZ-20-400	1,91	CLZ-FP-46/25	29	50	20	79	400	7%
RBZ-25-400	1,53	CLZ-FP-46/30	36	50	25	93	400	7%
RBZ-30-400	1,27	2 x CLZ-FP-46/19	43	50	30	124	400	7%
RBZ-40-400	0,95	2 x CLZ-FP-46/25	58	50	40	149	400	7%
RBZ-50-400	0,76	2 x CLZ-FP-46/30	72	50	50	189	400	7%
RBZ-60-400	0,63	3 x CLZ-FP-46/25	87	50	60	210	400	7%
RBZ-80-400	0,48	3 x CLZ-FP-46/33,3	115	50	80	241	400	7%
	RZ-10-400 RZ-12,5-400 RZ-15-400 RBZ-20-400 RBZ-25-400 RBZ-30-400 RBZ-40-400 RBZ-50-400 RBZ-60-400	RZ-10-400 3,83 RZ-12,5-400 3,05 RZ-15-400 2,55 RBZ-20-400 1,91 RBZ-25-400 1,53 RBZ-30-400 1,27 RBZ-40-400 0,95 RBZ-50-400 0,76 RBZ-60-400 0,63	RZ-10-400 3,83 CLZ-FP-46/12,5 RZ-12,5-400 3,05 CLZ-FP-46/15 RZ-15-400 2,55 CLZ-FP-46/19 RBZ-20-400 1,91 CLZ-FP-46/25 RBZ-25-400 1,53 CLZ-FP-46/19 RBZ-30-400 1,27 2 x CLZ-FP-46/19 RBZ-40-400 0,95 2 x CLZ-FP-46/25 RBZ-50-400 0,76 2 x CLZ-FP-46/25 RBZ-60-400 0,63 3 x CLZ-FP-46/25	RZ-10-400 3,83 CLZ-FP-46/12,5 15 RZ-12,5-400 3,05 CLZ-FP-46/15 18 RZ-15-400 2,55 CLZ-FP-46/19 22 RBZ-20-400 1,91 CLZ-FP-46/25 29 RBZ-25-400 1,53 CLZ-FP-46/30 36 RBZ-30-400 1,27 2 x CLZ-FP-46/19 43 RBZ-40-400 0,95 2 x CLZ-FP-46/25 58 RBZ-50-400 0,76 2 x CLZ-FP-46/30 72 RBZ-60-400 0,63 3 x CLZ-FP-46/25 87	RZ-10-400 3,83 CLZ-FP-46/12,5 15 50 RZ-12,5-400 3,05 CLZ-FP-46/19 22 50 RZ-15-400 2,55 CLZ-FP-46/25 29 50 RBZ-20-400 1,91 CLZ-FP-46/30 36 50 RBZ-30-400 1,27 2 x CLZ-FP-46/19 43 50 RBZ-40-400 0,95 2 x CLZ-FP-46/25 58 50 RBZ-50-400 0,63 3 x CLZ-FP-46/25 87 50	RZ-10-400 3,83 CLZ-FP-46/12,5 15 50 10 RZ-12,5-400 3,05 CLZ-FP-46/15 18 50 12,5 RZ-15-400 2,55 CLZ-FP-46/19 22 50 15 RBZ-20-400 1,91 CLZ-FP-46/25 29 50 20 RBZ-25-400 1,53 CLZ-FP-46/19 43 50 30 RBZ-30-400 1,27 2 x CLZ-FP-46/25 58 50 40 RBZ-40-400 0,95 2 x CLZ-FP-46/25 58 50 40 RBZ-50-400 0,76 2 x CLZ-FP-46/25 58 50 50 RBZ-60-400 0,63 3 x CLZ-FP-46/25 87 50 60	RZ-10-400 3,83 CLZ-FP-46/12,5 15 50 10 52 RZ-12,5-400 3,05 CLZ-FP-46/15 18 50 12,5 57 RZ-15-400 2,55 CLZ-FP-46/19 22 50 15 59 RBZ-20-400 1,91 CLZ-FP-46/25 29 50 20 79 RBZ-25-400 1,53 CLZ-FP-46/19 43 50 30 124 RBZ-30-400 1,27 2 x CLZ-FP-46/25 58 50 40 149 RBZ-40-400 0,95 2 x CLZ-FP-46/30 72 50 50 189 RBZ-50-400 0,63 3 x CLZ-FP-46/25 87 50 60 210	RZ-10-400 3,83 CLZ-FP-46/12,5 15 50 10 52 400 RZ-12,5-400 3,05 CLZ-FP-46/15 18 50 12,5 57 400 RZ-15-400 2,55 CLZ-FP-46/19 22 50 15 59 400 RBZ-20-400 1,91 CLZ-FP-46/25 29 50 20 79 400 RBZ-25-400 1,53 CLZ-FP-46/19 36 50 25 93 400 RBZ-30-400 1,27 2 x CLZ-FP-46/19 43 50 30 124 400 RBZ-40-400 0,95 2 x CLZ-FP-46/25 58 50 40 149 400 RBZ-50-400 0,76 2 x CLZ-FP-46/25 58 50 50 189 400 RBZ-60-400 0,63 3 x CLZ-FP-46/25 87 50 60 210 400

Circutor



Code:

Dimensions

×

Circutor