Page 1 of 2





GEDE EDC

GEDE EDC, PRIME PLC Concentrator

Code: Q67000.

> 2nd transformer connection: No

> Homologation: -

> Communications: PRIME

> Digital inputs: -

> LV supervisor: No

Description

The COMPACT DC concentrator is the device used to manage and read three-phase and single-phase power meters connected to the same low-voltage network using PRIME communications.

Typically located in the transformer substation, the COMPACT DC concentrator provides telemanagement features for the meters, whether reading the information they provide, or executing the actions that can be applied to this type of device, such as modifying tariffs, actuating the circuit breaker, etc.

COMPACT DC has an indirect three-phase meter with low-voltage monitoring functions, depending on the model.

The device features PRIME PLC communications, an Ethernet port and digital inputs.







GEDE EDC

PLC PRIME Concentrator

Code: Q67000.

Specifications

AC power supply			
Consumption	7 20 VA		
Frequency	50 / 60 Hz		
Nominal voltage	110 230 V~ ±20 %		
Mechanical characteristics			
Size (mm) width x height x depth	127 x 120 x 130 (mm)		
Envelope	Self-extinguishing V0 plastic		
Fastening	DIN rail		
Weight (kg)	1,25		
Environmental characteristics			
Protection class	IP40		
Relative humidity (without condensation)	5 95 %		
Storage temperature	-30 + 80 °C		
Working temperature	-25 +70 °C		
Communication Network			
Technology / Type	PRIME		
User interface			
LED	8 indication LEDs		
Standards			
Standards	UNE-EN 61000-4-2, UNE-EN 61000-4-3, UNE-EN 61000-4-4, UNE-EN 61000-4-5, UNE-EN 62052-11, IEC 61010		

GEDE EDC

PRIME PLC Concentrator

CODE	TYPE	2nd transformer connection	Homologation	Communications	Digital inputs	LV supervisor
Q67000.	GEDE EDC	No	-	PRIME	-	No
Q67540.	GEDE EDC-T 4I	No	Naturgy	PRIME	4	1
Q675A0.	GEDE EDC-T 4I4O	No	Naturgy	PRIME	4	1
Q67500.	GEDE EDC-T	No	Naturgy	PRIME	-	1

