

GEDE EDC-T 4G

GEDE EDC-T 4G, PRIME PLC Concentrator

Code: Q67550. **DESCATALOGADO**

> 2nd transformer connection: No

> Homologation: Naturgy

> Communications: PRIME | 4G

> Digital inputs: -

> LV supervisor: 1

Description

The **GEDE EDC** family concentrator is the device responsible for managing and reading three-phase and single-phase energy meters with PRIME communications connected to the same low-voltage network. The device can be configured for both PRIME 1.3.6 and PRIME 1.4, depending on the meters in its low-voltage network.

Typically located in the transformer substation, the **GEDE EDC** family concentrator enables remote management of the meters, either by reading the information they provide or by carrying out actions that can be applied to this type of device, such as changing tariffs or operating the Discon. relay, etc. The device also has an Ethernet port for external communications.

The **GEDE EDC** family comprises several concentrator models with additional features, such as an LV supervisor, digital inputs and outputs, etc.

Creation date: 24/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



GEDE EDC-T 4G

PLC PRIME concentrator, basic model.

Code: Q67550.

Specifications

AC power supply	
Consumption	10 ... 26 VA
Frequency	50 / 60 Hz
Nominal voltage	110 ... 230 V~ ±20 %

Mechanical characteristics	
Size (mm) width x height x depth	203 x 120 x 130 (mm)
Envelope	Self-extinguishing V0 plastic
Fastening	DIN rail
Weight (kg)	1,2

Environmental characteristics	
Protection class	IP40
Relative humidity (without condensation)	5 ... 95 %
Storage temperature	-30 ... + 80 °C
Working temperature	-25 ... +70 °C

Current measurement circuit	
Nominal current (In)	5 A

Voltage measurement circuit	
Maximum input voltage consumption	0.07 VA

Communication Network	
Technology / Interface	PRIME

Standards	
Electrical safety, Maximum height (m)	2000
Standards	UNE-EN 61000-4-2, UNE-EN 61000-4-3, UNE-EN 61000-4-4, UNE-EN 61000-4-5, UNE-EN 62052-11, IEC 61010

User interface	
LED	15 indication LEDs / 1 LED (20000 imp / kWh) / 1 LEDs (20000 imp / kVArh)

Radio communication -Antenna	
	SMA female connector

Radio communication	
Band	Cuatribanda/HSPA+HSPA/UMTS 850/900/1900/2100 MHz
Technology / Type	4G (Huawei MU609)

Creation date: 24/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



GEDE EDC-T 4G

PLC PRIME concentrator, basic model.

Code: Q67550.

GEDE EDC
PRIME PLC Concentrator

CODE	TYPE	2nd transformer connection	Homologation	Communications	Digital inputs	LV supervisor
Q67000.	GEDE EDC	No	-	PRIME	-	No
Q67540.	GEDE EDC-T 4I	No	Naturgy	PRIME	4	1
Q675A0.	GEDE EDC-T 4I4O	No	Naturgy	PRIME	4	1
Q67500.	GEDE EDC-T	No	Naturgy	PRIME	-	1
Q67570.	GEDE EDC-2T	Yes	Naturgy	PRIME	4	2

Creation date: 24/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.