



CirCAMP-2IP

CirCAMP-2IP, Energy Meter

Code: QM4001. (CONSULTAR DISPONIBILIDAD)

- > Communications: PLC
- > N° relays: 4
- > Digital inputs: 2
- > System: 2 indirect three-phase
- > Measurement Range (V): 3x127/220V... 3x230/400V
- > Measurement Range (A): .../5 A
- > Work mode: Post-pay/prepay

Description

CirCAMP-4DP is a compact meter with PLC communications that can be configured to read and manage up to 4 single-phase supplies independently, or one direct three-phase supply. Likewise, CirCAMP-2IP can be configured to manage up to 2 indirect three-phase supplies (.../5A), all in a single enclosure.

CirCAMP meters can work in Pre-payment or Post-payment mode, adapting to each type of use. Having cut-off systems for each channel enables the units to disconnect the supply each time the user consumes all the credits they had previously programmed, or manually disconnect when the user leaves the facility.

CirCAMP meters have 4 (4DP) or 2 (2IP) impulse-metering inputs for measuring water or other supplies and 4 relay outputs to operate electrovalves (and other control elements) and to cut off the supply independently. All models have PLC communications for readouts and management, enabling a simple installation that does not require communication wiring and that adapts completely to the existing installation.

Application

CirCAMP is designed to be installed in installations that need to control energy consumption, such as:

- Campsites
- Marinas
- Student residences
- Hotels
- Sports Centres



CirCAMP-2IP

Multi-function multiple meter with PLC communications

Code: QM4001.

Specifications

Mechanical characteristics

Size (mm) width x height x depth	192.5 x 120 x 79 (mm)
Weight (kg)	0,69