



DIR2

DIR2, Reactive relay

Code: R11211.

- > Alarm relay: No
- > Power supply (Vac): 400 Vac
- > Nr steps: 1
- > Input current: .../250 mA
- > Switching unit: Contactor

Description

The **DIR2** Power Factor Relay is capable of acting on a circuit in accordance with the reactive inductive or capacitive current transmitted through it. The **DIR2** relay measures reactive current in mA of the secondary of a .../250 mA current transformer **MC1** or **MC3** type. The front of the relay has a control panel that is used to adjust the reactive current where the relay will act. It has a LED that indicates the status of the relay.

Application

The **DIR2** relay is easy to install and program, making it the best solution in the following applications:

- o Individual compensation of small, medium or large power loads.
- o Partial compensation in installations with automatic equipment available.
- o Partial or total regulator in low-power installations. Instantaneous and total disconnection of capacitor banks when there is a high capacitive current in the network.
- o Control of reactive currents- capacitive and inductive - triggering an alarm signal when a high current is detected.



DIR2

Code: R11211.

Specifications

AC power supply	
Consumption	< 3 VA
Frequency	50-60 Hz
Nominal voltage	400 V ~ ±10%
Mechanical characteristics	
Size (mm) width x height x depth	35 x 85 x 73 (mm)
Weight (kg)	0,1
Environmental characteristics	
Protection class	IP 40
Relative humidity (without condensation)	95%
Working temperature	-10 ... +50 °C
Standards	
Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	EN 61010, EN 61000-3-2, EN 61000-3-3, EN 50081-2, EN 50082-1, EN 50082-2, EN 61000-4-2, EN 61000-4-4, EN 61000-4-8, EN 61000-4-5, EN 61000-4-11, UL 94
Current measurement circuit	
Consumption	< 0,05 VA
Nominal current (In)	0,25 A ~
Allowable overload	1,2 In
Permanent overload	1,2 In
Electrical safety	
Insulation	Double-insulated electric shock protection class II (IEC 61010-1)
Idle current tripping	
C/K trip adjustment range	0,15 ... 2
Connection delay Tc	5 s
Disconnection delay Tr	2 s
Digital relay outputs	
AC11 Ie/Ue	10 A / 250 V ~
DC11 Ie/Ue	0,3 A / 110 V dc
Thermal current (Ith)	10 A
Electrical life	10x10 ⁴ maniobras
Mechanical life	



DIR2

Code: R11211.

10x10⁶ operations

DIR2
Power factor relay 1 step. DIN rail

CODE	TYPE	Switching unit	Nr steps	Input current
R11211.	DIR2	Contactora	1	.../250 mA

Requires the use of MC transformers (not included). See section M - Measuring current transformers and shunts



DIR2

Code: R11211.

Dimensions

