



computer two

computer two, Power factor regulator

Code: R13820. DESCATALOGADO

- > Program: 1.1
- > Alarm relay: No
- > Measurement Range (V): 400
- > Power supply (Vac): 230 Vac (ph-N)
- > Nr steps: 2
- > Input current: .../250 mA
- > Switching unit: Contactor

Specifications

AC power supply	
Installation category	CAT III
Consumption	3 VA
Frequency	50-60 Hz
Nominal voltage	230 V ~ ±15%
Mechanical characteristics	
Size (mm) width x height x depth	90 x 90 x 5 (mm)
Environmental characteristics	
Relative humidity (without condensation)	95%
Working temperature	-10 ... +50 °C
Standards	
Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	IEC 61326-1 , IEC 61010-1 , UL 508
Current measurement circuit	
Nominal current (In)	0,25 A ~
Allowable overload	1,2 In
Permanent overload	1,2 In
Connection	Between V2 and N
Voltage measurement circuit	
Nominal voltage	400 V ~ ±15%
Electrical safety	
Insulation	Double-insulated electric shock protection class II (IEC 61010-1)
Digital relay outputs	
Electrical life	10x10 ⁴ maniobras



computer two

Code: R13820.

Mechanical life

5×10^6 operations

Requires the use of MC transformers (not included). See section M - Measuring current transformers and shunts