

computer two

computer two, Power factor regulator

Code: R13821. **DESCATALOGADO**

> Program: 1.1,5
> Alarm relay: No
> Measurement Range (V): 400
> Power supply (Vac): 230 Vac (ph-N)
> Nr steps: 2
> Input current: .../250 mA
> Switching unit: Contactor

Specifications

AC power supply

Installation category	CAT III
Consumption	3 VA
Frequency	50-60 Hz
Nominal voltage	230 V ~ ±15%

Mechanical characteristics

Size (mm) width x height x depth	90 x 90 x 5 (mm)
Weight (kg)	0,19

Environmental characteristics

Relative humidity (without condensation)	95%
Working temperature	-10 ... +50 °C

Standards

Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	IEC 61326-1 , IEC 61010-1 , UL 508

Current measurement circuit

Nominal current (In)	0,25 A ~
Allowable overload	1,2 In
Permanent overload	1,2 In
Connection	Between V2 and N

Voltage measurement circuit

Nominal voltage	400 V ~ ±15%

Electrical safety

Insulation	Double-insulated electric shock protection class II (IEC 61010-1)

Digital relay outputs

Electrical life	

Creation date: 20/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



computer two

Code: R13821.

	10x10 ^{4} maniobras
Mechanical life	5×10^{6} operations

Requires the use of MC transformers (not included). See section M - Measuring current transformers and shunts

Creation date: 20/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.