



computer two

computer two, Power factor regulator

Code: R13821. DESCATALOGADO

- > Program: 1.1,5
- > Alarm relay: No
- > Measurement Range (V): 400
- > Power supply (Vac): 230 Vac (ph-N)
- > Nr steps: 2
- > Input current: .../250 mA
- > Switching unit: Contactor

Specifications

AC power supply

Installation category	CAT III
Consumption	3 VA
Frequency	50-60 Hz
Nominal voltage	230 V ~ ±15%

Mechanical characteristics

Size (mm) width x height x depth	90 x 90 x 5 (mm)
Weight (kg)	0,19

Environmental characteristics

Relative humidity (without condensation)	95%
Working temperature	-10 ... +50 °C

Standards

Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	IEC 61326-1, IEC 61010-1, UL 508

Current measurement circuit

Nominal current (In)	0,25 A ~
Allowable overload	1,2 In
Permanent overload	1,2 In
Connection	Between V2 and N

Voltage measurement circuit

Nominal voltage	400 V ~ ±15%
-----------------	--------------

Electrical safety

Insulation	Double-insulated electric shock protection class II (IEC 61010-1)
------------	---

Digital relay outputs

Electrical life	
-----------------	--



computer two

Code: R13821.

10×10^4 maniobras

Mechanical life

5×10^6 operations

Requires the use of MC transformers (not included). See section M - Measuring current transformers and shunts