



computer SMART III Fast 12, Power factor regulator

Code: R13962.

> Alarm relay: Yes

> Communications: RS-485

> Measurement Range (V): 100...520

> I∆n (A): yes

> Power supply (Vac): 100...520 Vac

> Nr steps: 12

> Input current: .../5A | .../1A > Switching unit: EMF / EMB

Description

Measurement with three current transformers guarantees an analogue reading of the company meter. The Computer SMART III Fast reactive energy regulator is the only regulator on the market that offers the possibility of using 3 measurement transformers in addition to the conventional method of measuring with a single current transformer, as well as providing the functions of an integral power analyzer and controlling

Computer SMART III Fast is a regulator that ensures excellent preventive maintenance by means of programming its alarms and the options for testing the capacitor status, offering maximum supervision and safety of your compensation unit.

Application

Computer Smart III fast it's the ideal solution to compensate installations with a variation of quick load, between 40 ms and 4 seconds, and/or large unbalances between phases, such as welding units, cranes, lifts and lifting units, smelters, hospitals, automotive industry or any other sector or unit that requires an efficient compensation of the power factor.

The connection of 1 or 3 transformers makes computer SMART III Fast the perfect regulator in any installation, allowing the following:

- O Changing from 1 to 3 transformers in the following cases:
 - o Single-phase fast changing equipment
 - o Example: Single-phase welding
 - o Replacing the regulator of any capacitor bank
- \circ Perfect for installations with up to 4 objective cos φ , since it can adapt to any compensation need (different time periods).







Code: R13962.

Specifications

AC power supply	
Installation category	CAT III 300 V
Consumption	9 15 VA
Frequency	50 60 Hz
Nominal voltage	100 520 V ~
Mechanical characteristics	
Size (mm) width x height x depth	144 x 144 x 71 (mm)
Envelope	Plastic VO self-extinguishing
Fastening	Panel
Weight (kg)	0,545
Environmental characteristics	
Protection class	IP 51 (Front), IP 31 (unmounted)
Relative humidity (without condensation)	5 95%
Storage temperature	-20 +70 °C
Working temperature	-10 +55 °C
Current measurement circuit	
Installation category	CAT III 300 V
Nominal current (In)	/5A ó/1A
Phase current measuring range	1 120 % In
Minimum current measurement	50 mA
Voltage measurement circuit	
Installation category	CAT III 300 V
Sampling frequency	45 65 Hz
Input impedance	660 kΩ
Frequency measuring range	45 65 Hz
Voltage measuring range	20300 V Ph-N , 35520 V Ph-Ph
Nominal voltage	230 V Ph-N, 400 V Ph-Ph
Minimum measurement voltage (Vstart)	20 V F-N, 35 V F-F
Standards	
Electrical safety, Maximum height (m)	2000
Standards	IEC 61010, IEC 61000, IEC 61000-6-2, IEC 61000-6-4, Medidas conforme a : IEC 61557-12
User interface	
LED	4 LED







Code: R13962.

Keyboard	Capacitive, 5 keys
Display type	LCD Custom COG
Digital inputs	
Input/output insulation	Optoisolated
Quantity	2
Туре	Potential-free contact
Leakage current measurement (ID)	
Secondary nominal current	0,003 A
Minimum current measurement (Istart)	10 mA
Measurement range	0,01 1,5 A
Other digital transistor outputs	
Quantity	2
Туре	NPN
Maximum current	50 mA
Maximum voltage	24 Vcc
Digital relay outputs	
Quantity	2 (ventilador, alarma)
Maximum current	1A
Maximum open contact voltage	1 kV
Electrical life	30×10^3 ciclos
Mechanical life	5 x 10 ⁶ Cycles
Maximum switching capacity	2500 VA
5: "	
Digital transistor outputs	
Quantity	6
Туре	Opto MOSFET
Maximum current	150 mA
Maximum voltage	24 Vcc
Measurement accuracy	
Phase current measurement	0.5% ± 1 digit
Reactive energy measurement (kvarh)	Class 1
Reactive power measurement (kvar)	1% ± 2 digit
Active energy measurement (kWh)	Class 1
Active power measurement (kW)	0.5% ± 2 digits
Phase voltage measurement	0.5% ± 1 digit



Serial communication





Code: R13962.

Protocol	Modbus RTU
Technology / Type	RS-485

computer SMART III-Fast

Power factor controllers for static switching

CODE	TYPE	Switching unit	Nr steps	Input current	
R13953.	computer SMART III F6-12Vdc	EMB-2PH	6	/5A /1A	
R13964.	computer SMART III F12-12Vdc	EMB-2PH	12	/5A /1A	
R13951.	computer SMART III Fast 6	EMF / EMB	6	/5A /1A	
R13962.	computer SMART III Fast 12	EMF / EMB	12	/5A /1A	







Power factor controllers for static switching

Code: R13962.

Dimensions Connections







