



## CQ-40/40

---

CQ-40/40, Power Capacitor

Code: R2033J.

- > kvar 50 Hz: 40
- > kvar 60 Hz: 50
- > Frequency (Hz): 50
- > Use voltage (V): 400

### Description

---

The CQ dry-type prismatic capacitor range covers all power and voltage requirements, from 50 to 60 Hz. The design, manufacturing and testing processes of prismatic capacitors guarantee the production of top quality and long lasting capacitors. The 4 internal protection levels (self-regulation of the internal fuse, protection cover and vermiculite) make prismatic capacitors the safest units in the market.

### Application

---

Its application is based on the compensation in installations with fixed and variable loads (capacitor banks).



## CQ-40/40

Low voltage three-phase power capacitors

Code: R2033J.

### Specifications

#### AC power supply

Frequency	50 ó 60 Hz
-----------	------------

#### Electrical characteristics

Losses (W)	Dielectric: < 0,2 W / kvar Total: < 0,4 W / kvar
Discharge resistance	75 V / 3 min
Surge	10 % 8 h over 24 h 15 % up to 15 min over 24 hours 20 % up to 5 min over 24 hours 30 % up to 1 min over 24 hours
Tolerance C	-5 ... +15 %
Voltage	400 V
Insulation voltage, circuit	3 / 15 kV

#### Mechanical characteristics

Size (mm) width x height x depth	360 x 520 x 75 (mm)
Envelope	Treated and painted steel in RAL 3005 colour
Torque setting	15 Nm
Cable gauge at current terminals	Power M10 Earth M6
Fastening	Vertical. Minimum distance between condensers 4 cm
Ventilation	Natural or forced depending on the cabinet
Weight (kg)	8,5

#### Environmental characteristics

Protection class	IP 42 with terminal cover
Relative humidity (without condensation)	80%
Working temperature	T° class C: Daily average: 40 °C, annual average: 30 °C, maximum: 50 °C, minimum: -40 °C

#### Standards

Certifications	VDE 560
Electrical safety, Maximum height (m)	2000
Standards	IEC 60831-1, IEC 70/7, UNE-EN 20827, UNE-EN 20010, BS 1650

#### Current measurement circuit

Allowable overload	1,3 In
Permanent overload	1,3 In

#### Protection

Circuit breaker type	Dielectric regeneration Internal fuse Overpressure system Vermiculite
----------------------	---



## CQ-40/40

Low voltage three-phase power capacitors

Code: R2033J.

### CQ-50 Hz

Power capacitors for LV

CODE	TYPE	kvar 50 Hz	kvar 60 Hz	Use voltage (V)
<b>400 Vac</b>				
R2033C.	CQ-40/10	10	12.5	400
R2033D.	CQ-40/12,5	12.5	15	400
R2033E.	CQ-40/15	15	17.5	400
R2033F.	CQ-40/20	20	25	400
R2033G.	CQ-40/25	25	30	400
R2033H.	CQ-40/30	30	35	400
R2033J.	CQ-40/40	40	50	400
R2033K.	CQ-40/50	50	60	400
<b>440 Vac</b>				
R2034E.	CQ-44/15	15	17.5	440
R2034F.	CQ-44/20	20	25	440
R2034G.	CQ-44/25	25	30	440
R2034H.	CQ-44/30	30	35	440
R2034J.	CQ-44/40	40	50	440
R2034K.	CQ-44/50	50	60	440



## CQ-40/40

Low voltage three-phase power capacitors

Code: R2033J.

### Dimensions

