



CFB-46/37-6B

CFB-46/37-6B, Power capacitors for detuned filters

Code: R2425J.

- > kvar (400 V): 30
- > kvar (440 V): 40
- > For reactor: REZ-30-400
- > Use voltage (V): 400

Description

The application of new technologies have allowed CIRCUITOR to reinvent the classic CS capacitor. The spirit of innovation and proprietary technology used during the design of the new CSB capacitor have increased the lifespan of traditional prismatic capacitors by over 60%. This new series has improved all aspects of the previous models, offering our customers a longer-lasting, safer and more profitable capacitor.

Application

Its application is focused on the compensation of installations under fixed and variable loads (capacitor banks) with a high content of harmonics and/or the risk of resonance.



CFB-46/37-6B

Power capacitors for harmonics filters with static switching operation of the OPTIM FRE series

Code: R2425J.

Specifications

AC power supply

Frequency	50 ó 60 Hz
-----------	------------

Electrical characteristics

Permanent overload	1,3 In
Losses (W)	Dielectric: < 0,2 W / kvar Total: < 0,5 W / kvar
Discharge resistance	75 V / 3 min
Surge	10 % 8 h over 24 h 15 % up to 15 min over 24 hours 20 % up to 5 min over 24 hours 30 % up to 1 min over 24 hours
Tolerance C	-5 ... +15 %
Insulation voltage, circuit	3 / 15 kV

Mechanical characteristics

Size (mm) width x height x depth	360 x 330 x 120 (mm)
Envelope	Treated and painted steel in RAL 3005 colour
Thermal management	Natural or forced depending on the cabinet
Fastening	Vertical
Weight (kg)	7,1

Environmental characteristics

Protection class	IP 42 with terminal cover
Relative humidity (without condensation)	80%
Working temperature	T° class C: Daily average: 40 °C, annual average: 30 °C, maximum: 50 °C, minimum: -40 °C

Standards

Certifications	VDE 560
Electrical safety, Maximum height (m)	2000
Standards	IEC 60831-1, IEC 70/7, UNE-EN 20827, UNE-EN 20010, BS 1650

Protection

Circuit breaker type	Dielectric regeneration Internal fuse Overpressure system Vermiculite
----------------------	---

CFB-6B

Power capacitors for harmonics filters with static switching operation of the FRE series

CODE	TYPE	kvar (400 V)	kvar (440 V)	Use voltage (V)
400 Vac				



CFB-46/37-6B

Power capacitors for harmonics filters with static switching operation of the OPTIM FRE series

Code: R2425J.

CODE	TYPE	kvar (400 V)	kvar (440 V)	Use voltage (V)
R2425A.	CFB-46/6-6B	5	6,25	400
R2425D.	CFB-46/12,5-6B	10	12,5	400
R2425G.	CFB-46/25-6B	20	25	400
R2425J.	CFB-46/37-6B	30	40	400
R2425K.	CFB-46/50-6B	40	50	400
R2425L.	CFB-46/62-6B	50	60	400
R2425P.	CFB-46/74-6B	60	75	400
R2425R.	CFB-46/100-6B	80	100	400

NOTE: The capacitor has been sized for 460/260 V and a power that is 20 % higher than that indicated in kvar columns to compensate for the overvoltage effect of the reactor.