



## CMC 12 B

---

CMC 12 B, Contactor

Code: R281A6.

- > Dumping Resistors: 1
- > Frequency (Hz): 50 / 60
- > kvar 220-240V: 6.7
- > kvar 400-440-480 V: 12.5
- > kvar 500-550V: 15
- > kvar 660-690 V: 18
- > Coil voltage (Vac): 230

### Description

---

CMC-B series are contactors adjusted for switching single-step or multiple step capacitor banks. They have high operating times and a high electrical endurance that make the most robust and durable contactors.

### Application

---

They are installed in switching single-step or multiple step capacitor banks.



## CMC 12 B

Capacitor contactors

Code: R281A6.

### Specifications

#### AC power supply

Frequency	50/60 Hz
Nominal voltage	220 ... 690 V

#### Electrical characteristics

Cadence of manoeuvre	240/h
Nominal operating current	18.5 A (400 V)
Coil tension / tolerance	230 V / 0,85 ... 1,1 Un
Electrical lifetime	200000 cycles
Insulation voltage, circuit	690 ... 1000 V

#### Mechanical characteristics

Size (mm) width x height x depth	44.8 x 72.2 x 107.9 (mm)
Weight (kg)	0,32

#### Environmental characteristics

Protection class	IP 00
Relative humidity (without condensation)	5 ... 95 %
Working temperature	-25 ... +55 °C

#### Standards

Certifications	VDE
Electrical safety, Maximum height (m)	2000
Standards	IEC 60947-4-1, VDE 0660

#### CMC B

CMC-B contactors

CODE	TYPE	Frequency (Hz)	kvar 220-240V	kvar 400-440-480 V	kvar 500-550V	kvar 660-690 V
<b>Maximum operating power (Kvar)</b>						
R281A5.	CMC 7.5 B	50 / 60	5	7.5	9	11
R281A6.	CMC 12 B	50 / 60	6.7	12.5	15	18
R281A4.	CMC 20 B	50 / 60	11	20	24	30
R281A8.	CMC 32 B	50 / 60	14	25	30	35
R281A1.	CMC 40 B	50 / 60	20	30	35	40
R281A9.	CMC 75 B	50 / 60	29	50	60	70
R281A3.	CMC 85 B	50 / 60	32	60	70	80
R281AH.	CMC 150 D	50 / 60	45	80	100	115



## CMC 12 B

---

Capacitor contactors

Code: R281A6.

---