



OPTIM FRF-75-440

OPTIM FRF-75-440, Fixed capacitor with armonic filter

Code: R5X3A0.

- > Cable section (mm²): 50
- > kvar (400 V): 62
- > kvar (440 V): 75
- > Use voltage (V): 440

Description

The **FRF / FRM** Series capacitor banks with detuned filters have been designed for power compensation purposes in motors and transformers with a constant load level, a high content of harmonics and where there is a risk of resonance. Including:

- **FRF**: general protection with NH-00 fuses with a high rupture power (HRP) for the capacitor.
- **FRM**: general circuit breaker protection for the capacitor.

Application

Its application is mainly based on the compensation of transformers and motors. In general, it is used for the compensation of installations under constant loads and where there is a high content of harmonics in the network.



OPTIM FRF-75-440

Fixed capacitor with rejection reactance $p = 7\%$

Code: R5X3A0.

Specifications

Electrical characteristics

Losses (W)	Dielectric: < 0.2 W/kvar Total: < 0.5 W/kvar
Discharge resistance	75 V / 3 min
Surge	15 % 8 h over 24 h 15 % up to 15 min over 24 hours 20 % up to 5 min over 24 hours 30 % up to 1 min over 24 hours
Reinforcement voltage	440 V
Tolerance C	$\pm 10\%$

Mechanical characteristics

Size (mm) width x height x depth	650 x 1060 x 420 (mm)
Thermal management	Natural or forced according to options
Fastening	Vertical
Weight (kg)	85

Environmental characteristics

Protection class	IP 21
Relative humidity (without condensation)	80%

Current measurement circuit

Permanent overload	1,3 In
--------------------	--------

Standards

Electrical safety, Maximum height (m)	2000 m
---------------------------------------	--------

Features / performance

Components	CF capacitor General protection by fuse with high breaking capacity (APR). NH-00 series.
------------	--

Protection

Element	Individual protection of each step with fuses with high rupture power (HRP). NH-00 Series.
---------	--

OPTIM FRF

Fixed capacitors with detuned reactor of P = 7% (fres=189 Hz), 50 Hz

CODE	TYPE	kvar (400 V)	kvar (440 V)	Cable section (mm2)
OPTIM FRF, fuse protection APR, 440 V, 50 Hz				
R5X350.	OPTIM FRF-25-440	21	25	10
R5X370.	OPTIM FRF-37,5-440	31	37,5	16



OPTIM FRF-75-440

Fixed capacitor with rejection reactance $p = 7\%$

Code: R5X3A0.

CODE	TYPE	kvar (400 V)	kvar (440 V)	Cable section (mm ²)
R5X380.	OPTIM FRF-50-440	42	50	25
R5X390.	OPTIM FRF-60-440	50	60	35
R5X3A0.	OPTIM FRF-75-440	62	75	50
R5X3B0.	OPTIM FRF-100-440	83	100	70

See CFB capacitor and RZ /RBZ reactor components in the Low Voltage Capacitor and Reactor Section. Cable cross-section for installations with $U_n = 400$ V. The installation company must ensure compliance with the low voltage directive at all times, in accordance with the particularities of each installation and type of cable



OPTIM FRF-75-440

Fixed capacitor with rejection reactance $p = 7\%$

Code: R5X3A0.

Dimensions

