



FB3-5-06

FB3-5-06, Filter

Code: R78101. DESCATALOGADO

- > System: Single-phase
- > Frequency (Hz): 50
- > Max.neutral current: 6

Description

FB3 filters block 3rd order harmonics and have been designed to reduce these harmonics in installations with distorting singlephase loads.

Application

For single-phase loads, such as PCs, TFT screens, projectors, etc.



FB3-5-06

Third harmonic blocking filter
Code: R78101.

Specifications

AC power supply

Frequency	50 HZ (60 Hz bajo demanda)
Nominal voltage	220/240 Vca F-N

Mechanical characteristics

Size (mm) width x height x depth	204 x 310 x 233 (mm)
Weight (kg)	8

Environmental characteristics

Protection class	IP 23 (UNE-EN 60529)
Relative humidity (without condensation)	95%
Working temperature	-10 ... +50 °C

Electrical characteristics

Maximum transient current	10 A (1 min followed by at least 5 min to nominal)
---------------------------	--

Current measurement circuit

Allowable overload	6 A (in the set of sockets)
Permanent overload	6 A (in the set of sockets)