CPF-TE Sal.1,3

Code: M25321. DESCATALOGADO

- > Transducer FP
- > Output type: 1

> 3

> Analog output: 0...20mA

> System: Balanced three-phase (3 wires)

Description

The CPF transducers measure power factor single phase.

The analog output is directly proportional to the measurement signal, 0...20 mA or 4...20 mA. The analog output can be bidirectional.

Circutor



Power factor transducer

Code: M25321.

Specifications

AC power supply, insulation	
Pulse test (kV)	4 kV (1,2/50µs)
Test voltage (kV)	3 kV RMS 50 Hz 1min
AC power supply	
Consumption	2,5 VA
Frequency	4090 Hz
Nominal voltage	24/115/230/400 Vca (-15+20 %)
DC power supply, insulation	
Pulse test (kV)	3 kV (1,2/50µs)
Test voltage (kV)	2 kV RMS 50Hz 1 min
DC power supply	
Consumption	2,5 VA
Nominal voltage	9-18 / 18-36 Vdc 36-72 / 90-140 Vdc
Mechanical characteristics	
Size (mm) width x height x depth	95 x 72 x 110 (mm)
Weight (kg)	0,31
Environmental characteristics	
Protection class	IP 20 (Terminals) IP 40 (case)
Storage temperature	-40+70 °C
Working temperature	-10+55 °C
Current measurement circuit	
Nominal current (In)	5A
Phase current measurement	0,56 In
Allowable overload	300 % In permanent
Voltage measurement circuit	
Consumption	0,2 VA
Frequency measuring range	4565 Hz
Voltage measuring range	10150 % Vn
Nominal voltage	500 Vca
Maximum permanent measurement voltage	1000 V





Power factor transducer

Code: M25321.

Standards

Electrical safety, Maximum height (m)

2000

Circutor

Creation date: 15/07/2025 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons. It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



Power factor transducer

Code: M25321.

Standards	IEC 529, IEC 688, IEC 801, EN 50081-2, EN 50082-2, IEC 1010
Analogue inputs	
Load impedance in current	< 500 Ω
Ripple (effective RMS value)	< 0,5 %
Response time	< 500 ms (099 % Vn)
Analogue outputs	
Current mode, nominal range	020 mAac / 420 mAac
Measurement accuracy	
Phase current measurement	0,5 % FS

Circutor



Power factor transducer

Code: M25321.

Dimensions

×

