

CC-WG Out2, WG Transducer

Code: M25631. DESCATALOGADO

- > Output type: 2
- > Analog output: 4...20mA
- > Measure: 0 ... 3 Aac

Description

The CC-WG set transforms an A.C. Current (between 0 and 3 A) into a process signal.

The analog output is directly proportional to the true RMS input signal.

Circutor



AC Current converter (residual current)

Code: M25631.

Specifications

Pulse test (kV)	4 kV (1,2/50µs)
Test voltage (kV)	3 kV RMS 50 Hz 1min
AC power supply	
Consumption	2,5 VA
Frequency	4090 Hz
Nominal voltage	115/230/400 Vca (-15+20 %)
DC power supply, insulation	
Pulse test (kV)	3 kV (1,2/50µs)
Test voltage (kV)	2 kV RMS 50Hz 1 min
DC power supply	
Consumption	2,5 VA
Nominal voltage	9-18 / 18-36 Vdc 36-72 / 90-140 Vdc
Mechanical characteristics	
Size (mm) width x height x depth	40 x 72 x 110 (mm)
Weight (kg)	0,31
Environmental characteristics	
Protection class	IP 20 (Terminals) IP 40 (case)
Storage temperature	-40+70 °C
Working temperature	-10+60 °C
Current measurement circuit	
Consumption	0,2 VA
Nominal current (In)	0-3A (primary WG)
Phase current measurement	0150 % In
Allowable overload	300 % In permanent
Standards	
Electrical safety, Maximum height (m)	2000
Standards	IEC 529, IEC 688, IEC 801, IEC 44-1, IEC 1010
Analogue inputs	
Load impedance in current	< 500 Ω
Ripple (effective RMS value)	< 0,5 %

Circutor

Creation date: 29/06/2025 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons. It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



AC Current converter (residual current)

Code: M25631.

Load impedance in voltage	> 500 Ω	
Response time	< 300 ms (099 % Vn)	
Analogue outputs		
Current mode, nominal range	010, 20 mAac	
Displaced output	0,22 V / 210 V / 420 mA	

Phase current measurement

1 % Measurement

Circutor



AC Current converter (residual current)

Code: M25631.

Dimensions

×

