

TC-Power Net-70-1000



TC-Power Net-70-1000

Code: M52635. DESCATALOGADO

- > Power analyzer
- > Protocol: Modbus/RTU
- > Usefull diam.(mm): 70
- > Communications: RS-485
- > Max. Current (A): 1000

Specifications

AC power supply

| | |
|-----------------------|-----------------------|
| Installation category | CAT III 300/520 Vac |
| Consumption | 4.2 VA |
| Frequency | 50...60Hz |
| Nominal voltage | 400 Vc.a.(-15...+10%) |

Mechanical characteristics

| | |
|----------------------------------|-------------------------------|
| Size (mm) width x height x depth | 130 x 110 x 46 (mm) |
| Envelope | Self-extinguishing V0 plastic |
| Weight (kg) | 0,32 |

Environmental characteristics

| | |
|--|--------------|
| Protection class | IP 20 |
| Relative humidity (without condensation) | 5...95% |
| Working temperature | -10...+50 °C |

Standards

| | |
|--|--------------------------------|
| Certifications | UL, VDE |
| Electrical safety, Maximum height (m) | 2000 |
| Electrical safety, Installation category | CAT III 300V / 520V, IEC 61010 |
| Standards | IEC 44-1, UL 94, VDE 0414 |

Current measurement circuit

| | |
|-------------------------------|-----------|
| Nominal current (In) | 1000 A |
| Phase current measuring range | 10...100% |
| Permanent overload | 1.2 In |

Voltage measurement circuit

| | |
|-----------------------------------|-----------------------|
| Frequency measuring range | 45...65 Hz |
| Nominal voltage | 300V Ph-N, 520V Ph-Ph |
| Insulation voltage | 3 kV~ |
| Maximum input voltage consumption | 0,75 VA |

Electrical characteristics



TC-Power Net-70-1000

Code: M52635.

| | |
|-----------------------------|----------|
| Insulation voltage, circuit | 3 kVc.a. |
|-----------------------------|----------|

Electrical safety

| | |
|------------|---|
| Insulation | Double-insulated electric shock protection class II (IEC 61010-1) |
|------------|---|

Measurement accuracy

| | |
|---------------------------|-----------------|
| Power factor measurement | 0,5...1 |
| Phase voltage measurement | 0.5 % ±2 digits |

Serial communication

| | |
|-------------------|--------|
| Technology / Type | RS-485 |
|-------------------|--------|

It requires the following in the case of three-phase systems: 1 Power Net xx-xxx + 2 TC-Power Net xx-xxx. The Power Net system is based on the installation of a master unit (Power Net), with which the measurement is taken in the 3 voltage and neutral phases, and the L1 current is measured. To measure current L2 and L3, install 2 TC-Power Net units connected to the master unit. They feature RS-485 communications, using the Modbus/RTU protocol.