



LC L36-16A-480, Filter

Code: R732070070000 DESCATALOGADO

Load current (A): 16Frequency (Hz): 60Q (kvar): 4,55cabinet: LCL TH

#### Description

LCL filters have been specially designed to eliminate the harmonics from the current absorbed by 6-pulse power converters, such as frequency variators for motors, UPS, etc. These are essentially passive filters based on a series-parallel combination of inductances and capacitors, adapted to filter the input of power converters.

#### **Application**

- o Reduction of the current wave's distortion towards the network and the rest of the installation.
- o Compliance with the IEC 61000-3-4, IEC 61000-3-12, IEC 61800-3 and IEEE-519.
- Energy savings with the reduction of the root mean square current (RMS), thus reducing the kV·A demand.
- Increase of the working life of units above this location with the corresponding reduction of thermal losses generated.
- Limits current transients, preventing damages caused to the converter and overvoltage trips that affect production processes.



Page 1 of 4





Harmonic filter for power converters

Code: R732070070000

#### **Specifications**

AC power supply		
Frequency	60 Hz	
Nominal voltage	400 Vca /480 Vca F-F (otras tensiones, bajo demanda)	
Mechanical characteristics		
Size (mm) width x height x depth	365 x 570 x 217 (mm)	
Envelope	Treated and painted steel. Frame RAL 1013 / Doors RAL 3005	
Fastening	On the ground	
Environmental characteristics		
Protection class	IP 20	
Relative humidity (without condensation)	80%	
Installation, location, position.	Inside	
Operating temperature	+ 35 °C	
Electrical characteristics		
Nominal current voltage drop	< 2 %	
LC load current (RMS)	16 A	
Filtered current If (RMS)	6,4 A	
Residual current THD	Approx. 8%	
Current measurement circuit		
Allowable overload	1,5 Ic ( $\leq$ 1 min.) + Ic ( $\leq$ 5 min.) (at maximum operating temperature)	
Standards		
Standards	UNE-EN 60439 , UNE-EN60831 , IEC 61000-6-3 , IEC 61000-6-4, Class A	

#### LCL

Harmonic filters for power converters

CODE	TYPE	Load current (A)	Q (kvar)
400 V			
R73107.	LC L35-16A-400	16	3,27
R73119.	LC L35-220A-400	220	46,42
460 - 480 V			
R732140070000	LC L36-76A-480	76	22,77
R732150070000	LC L36-90A-480	90	26,56
R732160070000	LC L36-110A-480	110	30,36







Harmonic filters for power converters

Harmonic filter for power converters

Code: R732070070000

CODE	ТҮРЕ	Load current (A)	Q (kvar)
R732170070000	LC L36-150A-480	150	45,53
R732180070000	LC L36-180A-480	180	53,12
R732190070000	LC L36-220A-480	220	60,71
R732200070000	LC L36-260A-480	260	68,3
R732210070000	LC L36-320A-480	320	91,07

Please contact us for other current, frequency and/or voltage values Optional: Overcompensation kit








Harmonic filter for power converters

Code: R732070070000

#### Connections





Page 4 of 4