



BC96 0...10V

BC96 0...10V, Process Indicator

Code: M11833.

- > Scale: 90°, P1
- > Accuracy: 1,5
- > Full scale: 0...10 V
- > Modules: 96x96

Description

- Does not need an auxiliary power supply
- DIN boxes with dimensions: 48, 72, 96 and 144
- Precision class 1.5
- Measurement in DC of 0 ... 10 V, 0/4 ... 20 mA, .../60 mV
- Exchangeable scales for BC48, BC72, BC96, BM 45

Application

For the measurement of the mean value of voltages and currents in direct current circuits, even of the pulsating type, in a vast margin of values.



BC96 0...10V

Process indicators

Code: M11833.

Specifications

Mechanical characteristics

| | |
|----------------------------------|---------------------|
| Size (mm) width x height x depth | 96 x 96 x 4902 (mm) |
| Fastening | Panel |
| Weight (kg) | 0,114 |

BC-IP

Process indicators, 90°

| CODE | TYPE | Scale | Accuracy | Modules | Device | Full scale |
|---------|----------------|----------|----------|---------|--------|------------|
| M11813. | BC48 0...10V | 90° , P1 | 1,5 | 48x48 | BC48 | 0...10 V |
| M11812. | BC48 0...20mA | 90° , P1 | 1,5 | 48x48 | BC48 | 0...20 mA |
| M11811. | BC48 4...20mA | 90° , P1 | 1,5 | 48x48 | BC48 | 4...20 mA |
| M11823. | BC72 0...10V | 90° , P1 | 1,5 | 72x72 | BC72 | 0...10 V |
| M11822. | BC72 0...20mA | 90° , P1 | 1,5 | 72x72 | BC72 | 0...20 mA |
| M11821. | BC72 4...20mA | 90° , P1 | 1,5 | 72x72 | BC72 | 4...20 mA |
| M11833. | BC96 0...10V | 90° , P1 | 1,5 | 96x96 | | 0...10 V |
| M11832. | BC96 0...20mA | 90° , P1 | 1,5 | 96x96 | BC96 | 0...20 mA |
| M11831. | BC96 4...20mA | 90° , P1 | 1,5 | 96x96 | BC96 | 4...20 mA |
| M11843. | BC144 0...10V | 90° , P1 | 1,5 | 144x144 | | 0...10 V |
| M11842. | BC144 0...20mA | 90° , P1 | 1,5 | 144x144 | | 0...20 mA |
| M11841. | BC144 4...20mA | 90° , P1 | 1,5 | 144x144 | | 4...20 mA |

Scales included in the price (*) The 6-digit code includes the 4 ... 20 mA scale



BC96 0...10V

Process indicators

Code: M11833.

Connections

