



## HC144 45-55Hz 230V

HC144 45-55Hz 230V, Frequencymeter

Code: M12741.

- > Scale: 90°
- > Accuracy: 0,5
- > Measure: 45...55 Hz
- > Frequency (Hz): 45...55
- > Modules: 144x144

### Description

- Does not need an auxiliary power supply
- DIN box with dimensions: 48, 72, 96 and 144
- Class 0.5
- Built-in electronic converter

### Application

Accurate and easy reading of frequency in alternating current circuits. The distortion of voltage (we shall measure its frequency) can reach 15% of the nominal voltage in the third order harmonic, while the Class is not affected.



## HC144 45-55Hz 230V

Frequencymeters

Code: M12741.

### Specifications

#### Mechanical characteristics

Size (mm) width x height x depth	144 x 144 x 71.8 (mm)
Weight (kg)	0,425

#### Environmental characteristics

Protection class	Panel: IP 52 (Front), IP 00 (Terminals)
Storage temperature	-25...+40 °C
Working temperature	+10 ... +30 °C

#### Standards

Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	BS 89, UNE-EN 60051, IEC 144, UL94, DIN 43780, IEC 51, UNE 21318

#### Current measurement circuit

Allowable overload	1,5 In permanent / 15 In during 1s
--------------------	------------------------------------

#### Voltage measurement circuit

Consumption	2 ... 3 VA
Sampling frequency	50 ... 400 Hz
Nominal voltage	230 V ~

#### Electrical characteristics

Insulation voltage, circuit	2kV a 50 Hz < 1min entre mecanismo y caja
-----------------------------	---

#### Measurement accuracy

Accuracy	0,5 % FE
----------	----------

#### HC

Pointer type frequencymeters, 90°

CODE	TYPE	Scale	Accuracy	Modules	Measure	Frequency (Hz)
<b>HC72</b>						
M12721.	HC72 45-55Hz 230V	90°	0,5	72x72	45...55 Hz	45...55
<b>HC96</b>						
M12731.	HC96 45-55Hz 230V	90°	0,5	96x96	45...55 Hz	45...55
<b>HC144</b>						
M12741.	HC144 45-55Hz 230V	90°	0,5	144x144	45...55 Hz	45...55



## HC144 45-55Hz 230V

---

Frequencymeters

Code: M12741.

---



# HC144 45-55Hz 230V

Frequencymeters

Code: M12741.

## Dimensions

