Page 1 of 3





DC72B A (.../5A)

DC72B A (.../5A), Ammeter

Code: M20221. DESCATALOGADO

> Scale: ... / 5 Aca > System: AC

Digital instrument

> Measure: Direct: 5 Aac Transformer: .../ 5 Aac

> Mounting: Pannel > Modules: 72 x 72

Description

- o Fully programmable: scale, transformer ratio, etc. (except frequency meters)
- o Measurement of V, A, Hz or °C.
- $\circ~$ Measurement in true root mean square (TRMS), ac types. Excellent quality / price ratio
- o Measurement of maximum and minimum values
- o Optional relay output, depending on the type

Application

The high luminosity 4-digit digital display indicates the voltage, current, frequency or instantaneous temperature, with the maximum and minimum values of medium and low voltage lines.







DC72B A (.../5A)

Digital indicator for panel mounting

Code: M20221.

Specifications

AC power supply	
Consumption	4 VA
Frequency	4070 Hz.
Nominal voltage	115230 Vc.a. (± 10%)
Mechanical characteristics	
Size (mm) width x height x depth	72 x 72 x 85.5 (mm)
Envelope	ABS VO
Weight (kg)	0,21
Environmental characteristics	
Protection class	IP 20 (Terminals & case), IP 54 (Front), IP 65 (with front protection)
Storage temperature	0+65 °C
Working temperature	-40+70 °C
Current measurement circuit	
Input/output insulation	Tensión de prueba: 3 kV, 50Hz,1min / Test de impulsos: 4 kV (1,2/50 μs)
Number of samples per cycle	32
Resolution	10 bits
User interface	
Overscale indicator	
LED	2
Decimal point	Programable
Range	09999 (c.a.) / -19999999 (c.c.)
Display type	7 segments (4 digits)
Standards	
Standards	IEC 1010, IEC 348, IEC 664, EN50081-1, EN50082-1
Measurement accuracy	
Phase current measurement	± 0,5 % FS (± 1 digit)

DC-B

Digital instrument

CODE	TYPE	Scale	System	Measure	Modules

Ammeters / Process indicators









DC72B A (.../5A)

Digital instrument

Digital indicator for panel mounting

Code: M20221.

CODE	TYPE	Scale	System	Measure	Modules
M20226.	DC72B A (10A)	10 Acc	DC	Direct	72 x 72

All AC instruments measure TRMS values Please see the code table for other power supply values (110 Vdc power supply not available)

