

DM45-V, Voltmeter

Code: M20901. DESCATALOGADO

- > N° relays: 1
- > System: AC
- > Measure: 50...600 Vac
- > Paramètre: Voltmeter
- > Mounting: DIN rail

Description

- Electrical parameter indicator equipment
- $\circ~$ Its design enables the installation of the unit on small panels
- $\circ\;$ It measures voltage, current, frequency and harmonic distortion, depending on the type
- Fully sealed
- Fully programmable alarm relay
- Robust and compact
- Stores maximum and minimum values

Application

- Displays one or various electrical parameters of a sub-panel, control process or determined machine.
- Alarm system: the unit's internal relay can act on contactors, sound and/or light devices to carry out a protection or warning operation.

Circutor

398
0585 DMAS
6

Digital instruments, DIN rail

Code: M20901.

Specifications

AC power supply		
Consumption	5 VA	
Frequency	4070 Hz.	
Nominal voltage	115 / 230 Vc.a	
Mechanical characteristics		
Size (mm) width x height x depth	36 x 85 x 63.8 (mm)	
Envelope	Self-extinguishing ABS	
Weight (kg)	0,195	
Environmental characteristics		
Protection class	IP 20 / IP 54 with terminal cover (optional) (for models Ø 85, 100, 116 mm)	
Relative humidity (without condensation)	595 %	
Storage temperature	-40+70 °C	
Working temperature	-20+50 °C	
Voltage measurement circuit		
Consumption	0,6 VA	
Maximum permanent measurement voltage	1,05 Vn	
Minimum measurement voltage (Vstart)	50 Vac	
Maximum value	600 Vc.a.	
User interface		
LED	4	
Range	Valor máximo (600)	
Resolution of the display	30	
Display type	7 segments (4 digits), red	
Standards		
Standards	EN 61000-6-3, EN 61000-6-1, IEC 61010-1, IEC 60664	
Digital relay outputs		
Contact-coil insulation	2000 Vc.a.	
Contact-contact insulation	750 Vc.a.	
Nominal current	5 Aac	
Insulation resistance	> 1000 MΩ	
Resistive load (max.)	750 VA	
Maximum open contact voltage	250 Vac	



Creation date: 16/07/2025 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons. It accepts no liability for any errors, inaccuracies or possible lack of information in this document.



Digital instruments, DIN rail

Code: M20901.

Measurement accuracy

Phase current measurement

± 0,5 % FS (± 1 digit)

Other information of interest: Size: 2 modules



Digital instruments, DIN rail

Code: M20901.

Dimensions

Connections

×

×

