



## CVE-A-AP

CVE-A-AP, Transducer Vac.

Code: M25021. DESCATALOGADO

- > Output type: 1
- > Analog output: 0...20mA
- > Measure: 230 Vac
- > Paramètre: V ~

### Description

The **CVE-A** and **CVE-AP** transducers, convert A.C voltage to D.C process indicator signal.

The analog output is directly proportional to the input signal, calibrated as a RMS with sinus signal of 50Hz.



## CVE-A-AP

Narrow section AC Voltage transducer

Code: M25021.

### Specifications

#### AC power supply

Nominal voltage	0...5, 10 Vcc
-----------------	---------------

#### Mechanical characteristics

Size (mm) width x height x depth	20 x 70 x 110 (mm)
Weight (kg)	0,054

#### Environmental characteristics

Protection class	IP 20 (Terminals) IP 40 (case)
Storage temperature	-40...+70 °C
Working temperature	-10...+60 °C

#### Voltage measurement circuit

Consumption	2,5 VA
Frequency measuring range	45/65 Hz
Voltage measuring range	70...110 % Vn
Nominal voltage	0...660 V
Maximum permanent measurement voltage	120 % Vn

#### Standards

Electrical safety, Maximum height (m)	2000
Standards	IEC 529, IEC 688, IEC 801, EN 50081-1, EN 50082-1, IEC 1010

#### Analogue inputs

Load impedance in current	< 500 Ω
Ripple (effective RMS value)	< 2 %
Load impedance in voltage	> 500 Ω
Response time	< 300 ms (0...99 % Vn)

#### Analogue outputs

Current mode, nominal range	0...10, 20 mAac
Voltage mode: nominal output range	0...5, 10 Vac

#### Measurement accuracy

Phase current measurement	0,5 % FS
---------------------------	----------

#### CVE

Narrow section AC Voltage transducer



## CVE-A-AP

Narrow section AC Voltage transducer

Code: M25021.

CODE	TYPE	Output type	Analog output	System	Measure	Paramètre
<b>AC Voltage transducer</b>						
M25011.	CVE-A	2	4...20mA	-	300 Vac	V ~

Specify ACCORDING TO THE CODE TABLE: 1. Code / 2. Input range / 3. Output range / 4. Auxiliary power supply / 5. Specify the network voltage for CFE-AP. xxx-AP types external auxiliary supply not required. 4...20 mA output not possible.

For other values, see coding table on following pages




# CVE-A-AP

Narrow section AC Voltage transducer

Code: M25021.

## Dimensions



## Connections

