

### TCH6 250/5A

TCH6 250/5A, Current transformers high accuracy and narrow section

#### Code: M70433. CONSULTAR DISPONIBILIDAD

- > Flat strip(mm): 30 x 15 |20 x 10 |40 x 10
- > System: Single-phase
- > Class 0,2 Power (VA): 1,75
- > Class 0,2S Power (VA): 1,5
- > Class 0,5S Power (VA): 2,25
- > Measurement Range (A): 250/5
- > Input current: 250 A
- > Transformer type: Closed core

### Description

- Type: bar entrance
- $\circ~$  Types: from 40 to 4000 A
- $\circ~$  Internal diameter: from 20.3 to 63 mm, depending on the type
- $\circ~$  Busbar dimensions: from 25 x 5 mm to 30 x 100 mm
- Transformer certificate sheet is attached
- $\circ~$  Accessory on request for fixing on DIN rail (Types TCH6 and TCH6.2)
- $\circ~$  Secondary coding types .../5 A (on demand .../1 A.)

#### Application

Converting a high nominal current to a lower current so that it can be measured by the unit. In installations where the electrical supply can be interrupted to install transformers and a high accuracy is required.

# Circutor



### TCH6 250/5A

Current transformers narrow section and high accuracy

Code: M70433.

### Specifications

Safety factor (SF)	FS 5 1.75 VA (Class 0,2)		
Power			
Mechanical characteristics			
Size (mm) width x height x depth	66 x 87.7 x 71.4 (mm)		
Envelope	Plastic wrap V0 self-extinguishing, UL 94		
Weight (kg)	0,272		
Environmental characteristics			
Thermal Class	Class B (+130 °C)		
Protection class	IP 20		
Relative humidity (without condensation)	15 95 %		
Specific technical characteristics of current sensors			
Inner diameter Ø (mm)	28,5		
Operating voltage	0,72 kV~ max.		
Current measurement circuit			
Nominal frequency	50 / 60 Hz		
Primary current measurement	250 A		
Dynamic current (Idyn)	2,5 lth		
Thermal short-circuit current (Ith)	60 In		
Transformation ratio	/ 5 A		
Standards			
Standards	IEC 44-1, BS2627		

#### тсн

Current transformers narrow section and high accuracy

CODE	TYPE	Measurement Range (A)	Flat strip(mm)	Class 0,2 Power (VA)	Class 0,2S Power (VA)	Class 0,5S Power (VA)
TCH6.2						
M70444.	TCH6.2 200/5A	200/5	20 x 20  25 x 12  30 x 10	5	3,5	5

For other configurations see table of additional features





## TCH6 250/5A

Current transformers narrow section and high accuracy

Code: M70433.

### Dimensions





