

TC6 420 100A, Current transformers narrow section

Code: M72132. CONSULTAR DISPONIBILIDAD

- > Flat strip(mm): 40 x 10
- > Inner diameter (mm): 28
- > Analog output: 4...20 mA
- > Measurement Range (A): 100
- > Input current: 100 A
- > Transformer type: Current transformer with 4 ... 20 mA converter

Description

- Needs an output power supply of 7.5 ... 36 Vdc
- $\circ~$ Primary current: from 5 to 300 Aac, depending on the type
- Secondary current: 4 ... 20 mA
- $\circ~$ Internal diameter: from 20 to 44 mm, depending on the type
- $\circ~$ Busbar dimensions: from 25 x 5 mm to 60 x 12 mm

Application

Used in power lines to obtain a current proportional to the primary current rated at 0..20 mA / 4...20 mA in the secondary

Circutor



Current transformer with converter

Code: M72132.

Specifications

Auxiliary power supply			
Voltage	7,5 36 Vdc		
Electrical characteristics			
Safety factor (SF)	FS < 5		
Mechanical characteristics			
Size (mm) width x height x depth	64 x 80.5 x 44 (mm)		
Envelope	Plastic wrap VO self-extinguishing		
Weight (kg)	0,288		
Environmental characteristics			
Thermal Class	Class B (+130 °C)	Class B (+130 °C)	
Specific technical characteristics of current sensors			
Inner diameter Ø (mm)	28		
Operating voltage	0,72 kV~ max.	0,72 kV~ max.	
Current measurement circuit			
Nominal frequency	50 / 60 Hz		
Primary current measurement	200 A		
Dynamic current (Idyn)	2,5 lth		
Thermal short-circuit current (Ith)	60 In	60 In	
		4 20 mA	

TC-420

Current transformers with converter 4 \dots 20 mA or 0 \dots 20 mA

CODE	TYPE	Measurement Range (A)	Flat strip(mm)	Inner diameter (mm)
Output 420 mA	, ext. supply 7,536 Vdc			
M72112.	TC5 420 5A	5	25 x 5	20
M72113.	TC5 420 10A	10	25 x 5	20
M72114.	TC5 420 20A	20	25 x 5	20
M72134.	TC6 420 200A	200	40 x 10	28
M72136.	TC6 420 300A	300	40 x 10	28
M72131.	TC6 420 50A	50	40 x 10	28
M72152.	TC8 420 1000A	1000	60 x 12	44
M72153.	TC8 420 1500A	1500	60 x 12	44



Current transformer with converter

Code: M72132.

CODE	ТҮРЕ	Measurement Range (A)	Flat strip(mm)	Inner diameter (mm)
M72151.	TC8 420 500A	500	60 x 12	44

For greater currents, use: transformer + transducer

Circutor



Current transformer with converter

Code: M72132.

Dimensions

×

