



## Compact DC-S MINI

Compact DC-S MINI, PRIME PLC Concentrator

Code: Q4628C. [CONSULTAR DISPONIBILIDAD](#)

- > 2nd transformer connection: No
- > Homologation: -
- > Communications: PRIME
- > Digital inputs: -
- > LV supervisor: No

### Description

The **COMPACT DC** concentrator is the device used to manage and read three-phase and single-phase power meters connected to the same low-voltage network using PRIME communications.

Typically located in the transformer substation, the **COMPACT DC** concentrator provides telemanagement features for the meters, whether reading the information they provide, or executing the actions that can be applied to this type of device, such as modifying tariffs, actuating the circuit breaker, etc.

**COMPACT DC** has an indirect three-phase meter with low-voltage monitoring functions, depending on the model.

The device features PRIME PLC communications, an Ethernet port and digital inputs.



# Compact DC-S MINI

PLC PRIME Concentrator

Code: Q4628C.

## Specifications

### AC power supply

Installation category	CAT III 300V
Consumption	7 ... 20 VA
Frequency	50 / 60 Hz
Nominal voltage	110 ... 230 V~ ±20 %

### Mechanical characteristics

Size (mm) width x height x depth	127 x 120 x 130 (mm)
Envelope	Self-extinguishing V0 plastic
Fastening	DIN rail
Weight (kg)	0,876

### Environmental characteristics

Protection class	IP40
Relative humidity (without condensation)	5 ... 95 %
Storage temperature	-30 ... + 80 °C
Working temperature	-25 ... +70 °C

### Voltage measurement circuit

Frequency measuring range	45 ... 65 Hz
Voltage measuring range	127/220 ... 230/400 V~ ±20 %

### Communication Network

Technology / Interface	PRIME
------------------------	-------

### User interface

LED	8 indication LEDs
-----	-------------------

### Standards

Standards	UNE-EN 61000-4-2, UNE-EN 61000-4-3, UNE-EN 61000-4-4, UNE-EN 61000-4-5, UNE-EN 62052-11, IEC 61010
-----------	--

Isolated digital inputs, 10 kV/1 min




## Compact DC-S MINI

PLC PRIME Concentrator

Code: Q4628C.

### Dimensions



ESCALA 1:1

### Connections

