Cir-SET 340

,

Code: QS340

Description

El Cir-SET 130/320/340 es un registrador estático trifásico para la medida valores eléctricos como tensión, corriente, potencia activa y potencia reactiva con posibilidad de comunicaciones GSM/ GPRS, Ethernet, RS232 y RS485.
Cir-SET 130/320/340 adapta las nuevas tecnologías para ofrecer una gran versatilidad en programación, comunicaciones y módulos de expansión, dando como resultado un medidor adaptable a cualquier necesidad del usuario.

Application

Cir-SET is a 4-quadrant logger (consumption and generation), suitable for installation in electrical substations. The equipment offers 8 or 16 configurable variables to be stored in its internal memory (18,000 or 9,000 registers), in addition to multiple instantaneous registers through the ModBus RTU protocol.

Creation date: 06/09/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.

Cir-SET 340

Sub-station Recorder

Code: QS340

Specifications

Mechanical characteristics

Size (mm) width x height x depth	172 x 255 x 67 (mm)

Cir-SET-1/3
Fixed power analyzer

CODE	TYPE
Additional modules	
QS130	Cir-SET 130
QS320	Cir-SET 320
QS340	Cir-SET 340

Creation date: 06/09/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.