



## FB3T-5-25-00

FB3T-5-25-00, Harmonic Filter

Code: R78134. DESCATALOGADO

> System: Three-phase + Neutral

> Frequency (Hz): 50

> Max.neutral current: 25

### Description

FB3 filters block 3rd order harmonics and have been designed to reduce these harmonics in installations with distorting singlephase loads.

#### **Application**

For single-phase loads, such as PCs, TFT screens, projectors, etc.







# FB3T-5-25-00

Third harmonic blocking filter

Code: R78134.

## **Specifications**

Frequency	50 Hz Hasta 750 Vca	
Nominal voltage		
Mechanical characteristics		
Size (mm) width x height x depth	370 x 280 x 300 (mm)	
Environmental characteristics		
Protection class	IP 00	
	IP 00 95%	
Protection class		
Relative humidity (without condensation)	95%	









# FB3T-5-25-00


Third harmonic blocking filter

Code: R78134.

#### **Dimensions**







Туре	Α	В	C
FB3T-16	300	200	200
FB3T-50	370	280	300
FB3T-63	370	480	370
FB3T-100	650	1060	470
FB3T-63	370	480	370

