

SINUS-155-40-00

SINUS-155-40-00, Filter for PWM

Code: R7S008. (DESCATALOGADO)

> In (A): 155

> Switching Frequency (kHz): 10

Specifications

AC power supply

| | |
|-----------------|---------------|
| Frequency | 50 / 60 Hz |
| Nominal voltage | 380 / 400 Vca |

Mechanical characteristics

| | |
|----------------------------------|-----------------------------------|
| Size (mm) width x height x depth | 390 x 503 x 360 (mm) |
| Envelope | Copper conductor. Aluminium strip |

Environmental characteristics


| | |
|------------------|-------|
| Protection class | IP 00 |
|------------------|-------|

Electrical characteristics

| | |
|-----------------------------|--------------|
| Switching frequency | 2 ... 10 kHz |
| Maximum transient current | 2 In |
| Insulation voltage, circuit | 2 kV |

Current measurement circuit

| | |
|----------------------|-------------|
| Nominal current (In) | 4 ... 400 A |
| Permanent overload | 1,17 In |



SINUS-155-40-00

Filter for PWM

Code: R7S008.